Pioneer sound.vision.soul

Service Manual



DEH-P860MP/XN/UC

ORDER NO.
CRT3217

MULTI-CD CONTROL DSP HIGH POWER CD/MP3/WMA PLAYER WITH FM/AM TUNER

DEH-P860MP/XN/UC
DEH-P8600MP/XN/UC
DEH-P8650MP/XN/ES

This service manual should be used together with the following manual(s):

Model No.	Order No.	Mech.Module	Remarks
CX-3098	CRT3179	S10WMAcode2	CD Mech. Module:Circuit Description, Mech. Description, Disassembly

For details, refer to "Important symbols for good services".

PIONEER CORPORATION 4-1, Meguro 1-chome, Meguro-ku, Tokyo 153-8654, Japan
PIONEER ELECTRONICS (USA) INC. P.O. Box 1760, Long Beach, CA 90801-1760, U.S.A.
PIONEER EUROPE NV Haven 1087, Keetberglaan 1, 9120 Melsele, Belgium
PIONEER ELECTRONICS ASIACENTRE PTE. LTD. 253 Alexandra Road, #04-01, Singapore 159936

K-ZZD.MAR. 2004 printed in Japan

SAFETY INFORMATION

CAUTION

This service manual is intended for qualified service technicians; it is not meant for the casual do-it-yourselfer. Qualified technicians have the necessary test equipment and tools, and have been trained to properly and safely repair complex products such as those covered by this manual.
Improperly performed repairs can adversely affect the safety and reliability of the product and may void the warranty. If you are not qualified to perform the repair of this product properly and safely, you should not risk trying to do so and refer the repair to a qualified service technician.

WARNING

This product contains lead in solder and certain electrical parts contain chemicals which are known to the state of California to cause cancer, birth defects or other reproductive harm.
Health & Safety Code Section 25249.6 - Proposition 65

● CD Player Service Precautions

1. Before disassembling the unit, be sure to turn off the power. Unplugging and plugging the connectors during power-on mode may damage the ICs inside the unit.
2. To protect the pickup unit from electrostatic discharge during serviving, take an appropriate treatment(shorting-solder) by referring to "the DISASSEMBLY" on page 62.
3. After replacing the pickup unit, be sure to check the grating.(See p.58.)

[Important symbols for good services]
In this manual, the symbols shown-below indicate that adjustments, settings or cleaning should be made securely.
When you find the procedures bearing any of the symbols, be sure to fulfill them:

1. Product safety

You should conform to the regulations governing the product (safety, radio and noise, and other regulations), and should keep the safety during servicing by following the safety instructions described in this manual.

2. Adjustments

To keep the original performances of the product, optimum adjustments or specification confirmation is indispensable. In accordance with the procedures or instructions described in this manual, adjustments should be performed.

3. Cleaning

For optical pickups, tape-deck heads, lenses and mirrors used in projection monitors, and other parts requiring cleaning, proper cleaning should be performed to restore their performances.

4. Shipping mode and shipping screws

To protect the product from damages or failures that may be caused during transit, the shipping mode should be set or the shipping screws should be installed before shipping out in accordance with this manual, if necessary.

5. Lubricants, glues, and replacement parts

Appropriately applying grease or glue can maintain the product performances. But improper lubrication or applying glue may lead to failures or troubles in the product. By following the instructions in this manual, be sure to apply the prescribed grease or glue to proper portions by the appropriate amount.For replacement parts or tools, the prescribed ones should be used.

COMPACT disc DIGITAL AUDIO TEXT

Designed for Windows Media™

CONTENTS

1. SPECIFICATIONS

● DEH-P860MP/XN/UC

General

Power source ..... 14.4 V DC (10.8 – 15.1 V allowable)
Grounding system ..... Negative type
Max. current consumption
..... 10.0 A
Backup current ..... 5 mA or less
Dimensions (W × H × D):
DIN
Chassis ..... 178 × 50 × 159 mm (7 × 2 × 6-1/4 in.)
Nose ..... 188 × 58 × 29 mm (7-3/8 × 2-1/4 × 1-1/8 in.)
D
Chassis ..... 178 × 50 × 164 mm (7 × 2 × 6-1/2 in.)
Nose ..... 170 × 45 × 24 mm (6-3/4 × 1-3/4 × 1 in.)
Weight ..... 1.6 kg (3.5 lbs)

Audio/DSP

Continuous power output is 22 W per channel minimum into 4 ohms, both channels driven 50 to 15,000 Hz with no more than 5% THD.
Maximum power output ..... 50 W × 4
Load impedance ..... 4 Ω (4 – 8 Ω allowable)
Preout max output level/output impedance
..... 6.5 V/100 Ω
Loudness contour ..... +10 dB (100 Hz), +6.5 dB (10 kHz) (volume: –30 dB)
Equalizer (13-Band Graphic Equalizer):
Frequency ..... 50/80/125/200/315/500/800 Hz
1.25/2/3.15/5/8/12.5 kHz
Equalization range ..... ±12 dB
Auto equalizer (just for standard mode):
(Front & rear & subwoofer 13 band graphic)
Frequency ..... 50/80/125/200/315/500/800 Hz
1.25/2/3.15/5/8/12.5 kHz
Equalization range ..... +6 – –12 dB
Network (standard mode):
HPF (Front/rear):
Frequency ..... 50/63/80/100/125/160/200 Hz
Slope ..... 0 (Pass)/–6/–12 dB/oct
Gain ..... 0 – –24 dB/Mute
Subwoofer:
Frequency ..... 50/63/80/100/125/160/200 Hz
Slope ..... –6/–12/–18 dB/oct
Gain ..... +6 – –24 dB/Mute
Phase ..... Normal/Reverse
Network (3-way network mode):
High HPF:
Frequency ..... 1.6/2/2.5/3.15/4/5/6.3/8/10/12.5/16 kHz
Slope ..... –6/–12/–18/–24 dB/oct
Gain ..... 0 – –24 dB/Mute
Phase ..... Normal/Reverse
Mid HPF/LPF:
Frequency (LPF) ... 1.6/2/2.5/3.15/4/5/6.3/8/10/12.5/16 kHz
Frequency (HPF)
..... 31.5/40/50/63/80/100/125/160/200 Hz
Slope ..... 0 (Pass)/–6/–12/–18/–24 dB/oct
Gain ..... 0 – –24 dB/Mute
Phase ..... Normal/Reverse
Low LPF:
Frequency ..... 31.5/40/50/63/80/100/125/160/200 Hz
Slope ..... –12/–18/–24/–30/–36 dB/oct
Gain ..... +6 – –24 dB/Mute
Phase ..... Normal/Reverse

CD player

System ..... Compact disc audio system
Usable discs ..... Compact disc
Signal format:
Sampling frequency ..... 44.1 kHz
Number of quantization bits
..... 16; linear
Frequency characteristics ... 5 – 20,000 Hz (±1 dB)
Signal-to-noise ratio ..... 100 dB (1 kHz) (IHF-A network)
Dynamic range ..... 95 dB (1 kHz)
Number of channels ..... 2 (stereo)
MP3 decoding format ..... MPEG-1 & 2 Audio Layer 3
WMA decoding format ..... Ver. 7, 7.1, 8, 9 (2ch audio)
WAV signal format ..... Linear PCM & MS ADPCM

FM tuner

Frequency range ..... 87.9 – 107.9 MHz
Usable sensitivity ..... 8 dBf (0.7 μV/75 Ω, mono, S/N: 30 dB)
50 dB quieting sensitivity ..... 10 dBf (0.9 μV/75 Ω, mono)
Signal-to-noise ratio ..... 75 dB (IHF-A network)
Distortion ..... 0.3 % (at 65 dBf, 1 kHz, stereo)
0.1 % (at 65 dBf, 1 kHz, mono)
Frequency response ..... 30 – 15,000 Hz (±3 dB)
Stereo separation ..... 45 dB (at 65 dBf, 1 kHz)
Selectivity ..... 80 dB (±200 kHz)
Three-signal intermodulation (desired signal level)
..... 30 dBf (two undesired signal level: 100 dBf)

AM tuner

Frequency range ..... 530 – 1,710 kHz (10 kHz)
Usable sensitivity ..... 18 μV (S/N: 20 dB)
Signal-to-noise ratio ..... 65 dB (IHF-A network)

● DEH-P8600MP/XN/UC

General

Power source ..... 14.4 V DC (10.8 – 15.1 V allowable)
Grounding system ..... Negative type
Max. current consumption
..... 10.0 A

Backup currenr ..... 5 mA or less

Dimensions (W × H × D):
DIN
Chassis ..... 178 × 50 × 159 mm (7 × 2 × 6-1/4 in.)
Nose ..... 188 × 58 × 29 mm (7-3/8 × 2-1/4 × 1-1/8 in.)
D
Chassis ..... 178 × 50 × 164 mm (7 × 2 × 6-1/2 in.)
Nose ..... 170 × 45 × 24 mm (6-3/4 × 1-3/4 × 1 in.)
Weight ..... 1.6 kg (3.5 lbs)

Audio/DSP

Continuous power output is 22 W per channel minimum into 4 ohms, both channels driven 50 to 15,000 Hz with no more than 5% THD.
Maximum power output ..... 50 W × 4
Load impedance ..... 4 Ω (4 – 8 Ω allowable)
Preout max output level/output impedance
..... 4.0 V/100 Ω
Loudness contour ..... +10 dB (100 Hz), +6.5 dB (10 kHz) (volume: –30 dB)
Equalizer (13-Band Graphic Equalizer):
Frequency ..... 50/80/125/200/315/500/800 Hz
1.25/2/3.15/5/8/12.5 kHz
Equalization range ..... ±12 dB
Auto equalizer:
(Front & rear & subwoofer 13 band graphic)
Frequency ..... 50/80/125/200/315/500/800 Hz
1.25/2/3.15/5/8/12.5 kHz
Equalization range ..... +6 – –12 dB
HPF (Front/rear):
Frequency ..... 50/63/80/100/125/160/200 Hz
Slope ..... 0 (Pass)/–6/–12 dB/oct
Gain ..... 0 – –24 dB/Mute
Subwoofer:
Frequency ..... 50/63/80/100/125/160/200 Hz
Slope ..... –6/–12/–18 dB/oct
Gain ..... +6 – –24 dB/Mute
Phase ..... Normal/Reverse

CD player

System ..... Compact disc audio system
Usable discs ..... Compact disc
Signal format:
Sampling frequency ..... 44.1 kHz
Number of quantization bits
..... 16; linear
Frequency characteristics ... 5 – 20,000 Hz (±1 dB)
Signal-to-noise ratio ..... 100 dB (1 kHz) (IHF-A network)
Dynamic range ..... 95 dB (1 kHz)
Number of channels ..... 2 (stereo)
MP3 decoding format ..... MPEG-1 & 2 Audio Layer 3
WMA decoding format ..... Ver. 7, 7.1, 8, 9 (2ch audio)
WAV signal format ..... Linear PCM & MS ADPCM

FM tuner

Frequency range ..... 87.9 – 107.9 MHz
Usable sensitivity ..... 8 dBf (0.7 μV/75 Ω, mono, S/N: 30 dB)
50 dB quieting sensitivity ..... 10 dBf (0.9 μV/75 Ω, mono)
Signal-to-noise ratio ..... 75 dB (IHF-A network)
Distortion ..... 0.3 % (at 65 dBf, 1 kHz, stereo)
0.1 % (at 65 dBf, 1 kHz, mono)
Frequency response ..... 30 – 15,000 Hz (±3 dB)
Stereo separation ..... 45 dB (at 65 dBf, 1 kHz)
Selectivity ..... 80 dB (±200 kHz)
Three-signal intermodulation (desired signal level)
..... 30 dBf (two undesired signal level: 100 dBf)

AM tuner

Frequency range ..... 530 – 1,710 kHz (10 kHz)
Usable sensitivity ..... 18 μV (S/N: 20 dB)
Signal-to-noise ratio ..... 65 dB (IHF-A network)

Note

Specifications and the design are subject to possible modifications without notice due to improvements. ▣

● DEH-P8650MP/XN/ES

General

Rated power source ..... 14.4 V DC (allowable voltage range: 12.0 – 14.4 V DC)
Grounding system ..... Negative type
Max. current consumption ..... 10.0 A
Backup current ..... 5 mA or less

Dimensions (W × H × D):
- DIN
  - Chassis ..... 178 × 50 × 159 mm
  - Nose ..... 188 × 58 × 29 mm
- D
  - Chassis ..... 178 × 50 × 164 mm
  - Nose ..... 170 × 45 × 24 mm

Weight ..... 1.6 kg

Audio/DSP

Continuous power output is 22 W per channel minimum into 4 ohms, both channels driven 50 to 15,000 Hz with no more than 5% THD.
Maximum power output ..... 50 W × 4
Load impedance ..... 4 Ω (4 – 8 Ω allowable)
Preout max output level/output impedance ..... 6.5 V/100 Ω
Loudness contour ..... +10 dB (100 Hz), +6.5 dB (10 kHz) (volume: –30 dB)
Equalizer (13-Band Graphic Equalizer):
- Frequency ..... 50/80/125/200/315/500/800 Hz
  1.25/2/3.15/5/8/12.5 kHz
- Equalization range ..... ±12 dB

Auto equalizer (just for standard mode):
(Front & rear & subwoofer 13 band graphic)
- Frequency ..... 50/80/125/200/315/500/800 Hz
  1.25/2/3.15/5/8/12.5 kHz
- Equalization range ..... +6 – –12 dB

Network (standard mode):
- HPF (Front/rear):
  - Frequency ..... 50/63/80/100/125/160/200 Hz
  - Slope ..... 0 (Pass)/–6/–12 dB/oct
  - Gain ..... 0 – –24 dB/Mute
- Subwoofer:
  - Frequency ..... 50/63/80/100/125/160/200 Hz
  - Slope ..... –6/–12/–18 dB/oct
  - Gain ..... +6 – –24 dB/Mute
  - Phase ..... Normal/Reverse

Network (3-way network mode):
- High HPF:
  - Frequency ..... 1.6/2/2.5/3.15/4/5/6.3/8/10/12.5/16 kHz
  - Slope ..... –6/–12/–18/–24 dB/oct
  - Gain ..... 0 – –24 dB/Mute
  - Phase ..... Normal/Reverse
- Mid HPF/LPF:
  - Frequency (LPF) ... 1.6/2/2.5/3.15/4/5/6.3/8/10/12.5/16 kHz
  - Frequency (HPF) ..... 31.5/40/50/63/80/100/125/160/200 Hz
  - Slope ..... 0 (Pass)/–6/–12/–18/–24 dB/oct
  - Gain ..... 0 – –24 dB/Mute
  - Phase ..... Normal/Reverse
- Low LPF:
  - Frequency ..... 31.5/40/50/63/80/100/125/160/200 Hz
  - Slope ..... –12/–18/–24/–30/–36 dB/oct
  - Gain ..... +6 – –24 dB/Mute
  - Phase ..... Normal/Reverse

CD player

System ..... Compact disc audio system
Usable discs ..... Compact disc
Signal format:
- Sampling frequency ..... 44.1 kHz
- Number of quantization bits ..... 16; linear

Frequency characteristics ... 5 – 20,000 Hz (±1 dB)
Signal-to-noise ratio ..... 100 dB (1 kHz) (IEC-A network)
Dynamic range ..... 95 dB (1 kHz)
Number of channels ..... 2 (stereo)
MP3 decoding format ..... MPEG-1 & 2 Audio Layer 3
WMA decoding format ..... Ver. 7, 7.1, 8, 9 (2ch audio)
WAV signal format ..... Linear PCM & MS ADPCM

FM tuner

Frequency range ..... 87.5 – 108.0 MHz
Usable sensitivity ..... 8 dBf (0.7 μV/75 Ω, mono, S/N: 30 dB)
50 dB quieting sensitivity ..... 10 dBf (0.9 μV/75 Ω, mono)
Signal-to-noise ratio ..... 75 dB (IEC-A network)
Distortion ..... 0.3 % (at 65 dBf, 1 kHz, stereo)
0.1 % (at 65 dBf, 1 kHz, mono)
Frequency response ..... 30 – 15,000 Hz (±3 dB)
Stereo separation ..... 45 dB (at 65 dBf, 1 kHz)

AM tuner

Frequency range ..... 531 – 1,602 kHz (9 kHz)
530 – 1,640 kHz (10 kHz)
Usable sensitivity ..... 18 μV (S/N: 20 dB)
Signal-to-noise ratio ..... 65 dB (IEC-A network)

Infrared remote control

Wavelength ..... 940 nm ±50 nm
Output ..... typ; 12 mw/sr per Infrared LED

Note

Specifications and the design are subject to possible modifications without notice due to improvements. ■

2. EXPLODED VIEWS AND PARTS LIST

*NOTES : • Parts marked by " * " are generally unavailable because they are not in our Master Spare Parts List.*
• Screw adjacent to ▽ mark on the product are used for disassembly.
• For the applying amount of lobricants or glue, follow the instructions in this manual.
(In the case of no amount instructions,apply as you think it appropriate.)

2.1 PACKING(DEH-P860MP/XN/UC,DEH-P8600MP/XN/UC)



(1) PACKING(DEH-P860MP/XN/UC,DEH-P8600MP/XN/UC) SECTION PARTS LIST

Mark	No.	Description	Part No.
	1	Cord Assy	See Contrast table(2)
	2	Cord Assy	CDE7701
	3	Accessory Assy	CEA4302
	4	Spring	CBH1650
	5	Screw Assy	CEA4303
	6	Screw	CBA1650
	7	Bolt(M5x16)	CBA1783
*	8	Polyethylene Bag	CEG-127
	9	Screw	CRZ50P090FTC
	10	Screw	JPZ20P060FZK
	11	Nut	NF50FTC
	12	Screw	TRZ50P080FTC
*	13	Polyethylene Bag	CEG-158
	14	Handle	CNC5395
	15	Strap	CNC5402
	16	Bush	CNV3930
	17-1	Polyethylene Bag	CEG1116
	17-2	Owner's Manual	See Contrast table(2)
	17-3	Installation Manual	See Contrast table(2)
*	17-4	Causion Card	CRP1308
	17-5	Causion Card	CRP1310
*	17-6	Warranty Card	See Contrast table(2)
*	17-7	Card	See Contrast table(2)
	18	Polyethylene Bag	CEG1173
	19	Carton	See Contrast table(2)
	20	Sub Carton	CHG5195
	21	Contain Box	See Contrast table(2)
	22	Protector	CHP2546
	23	Protector	CHP2797
	24	Protector	CHP2798
	25	Protector	CHP2812
	26	Microphone Assy	CPM1054
	27	Case Assy	CXB3520
	28	Remote Control Unit	CXC2665

(2) CONTRAST TABLE

DEH-P860MP/XN/UC and DEH-P8600MP/XN/UC are constructed the same except for the following:

Mark	NO	Description	DEH-P860MP/XN/UC	DEH-P8600MP/XN/UC
	1	Cord Assy	CDE7436	CDE7437
	17-2	Owner's Manual	CRD3828	CRD3830
	17-3	Installation Manual	CRD3829	CRD3831
*	17-6	Warranty Card	CRY1070	Not used
*	17-7	Card	Not used	ARY1048
	19	Carton	CHG5194	CHG5193
	21	Contain Box	CHL5194	CHL5193

Owner's Manual,Installation Manual

Part No.	Language
CRD3828	English, French
CRD3829	English, French
CRD3830	English, French
CRD3831	English, French

2.2 PACKING(DEH-P8650MP/XN/ES)



● PACKING(DEH-P8650MP/XN/ES) SECTION PARTS LIST

Mark	No.	Description	Part No.
	1	Cord Assy	CDE7436
	2	Cord Assy	CDE7701
	3	Accessory Assy	CEA4301
	4	Spring	CBH1650
	5	Screw Assy	CEA3849
	6	Screw	CBA1650
	7	•••••	
*	8	Polyethylene Bag	CEG-127
	9	Screw	CRZ50P090FTC
	10	•••••	
	11	•••••	
	12	Screw	TRZ50P080FTC
*	13	Polyethylene Bag	CEG-158
	14	Handle	CNC5395
	15	•••••	
	16	Bush	CNV3930
	17-1	Polyethylene Bag	CEG1116
	17-2	Owner's Manual	CRD3832
	17-3	Owner's Manual	CRD3833
	17-4	Owner's Manual	CRB1902
	17-5	Installation Manual	CRD3834
*	17-6	Causion Card	CRP1308
	17-7	Causion Card	CRP1310
	18	Polyethylene Bag	CEG-162
	19	Carton	CHG5192
	20	Sub Carton	CHG5195
	21	Contain Box	CHL5192
	22	Protector	CHP2546
	23	Protector	CHP2797
	24	Protector	CHP2798
	25	Protector	CHP2812
	26	Microphone Assy	CPM1054
	27	Case Assy	CXB3520
	28	Remote Control Unit	CXC2665

● Owner's Manual,Installation Manual

Part No.	Language
CRD3832	English, Spanish
CRD3833	Portuguese(B), Traditional Chinese
CRB1902	Arabic
CRD3834	English, Spanish, Portuguese(B), Traditional Chinese, Arabic

2.3 EXTERIOR(1)



(1) EXTERIOR(1) SECTION PARTS LIST

Mark	No.	Description	Part No.
	1	Screw(M2x2.5)	CBA1641
	2	Screw(M2.6x4)	CBA1769
	3	Drive Unit	See Contrast table(2)
	4	Screw	BMZ26P040FTC
	5	Screw	CBA1633
	6	Spring	CBL1632
	7	Cord	CDE7392
	8	Holder	CND1848
	9	Holder	CND1850
	10	Insulator	CNM8797
	11	Gear	CNV7752
	12	Gear	CNV7753
	13	Gear	CNV7754
	14	Gear	CNV7755
	15	Switch Unit	CWS1389
	16	Switch(S1)	CSN1051
	17	Spring Switch(S2)	CSN1052
	18	Holder Unit	CXC2196
	19	Holder Unit	CXC2197
	20	Arm Unit	CXC2198
	21	Arm Unit	CXC2199
	22	Arm Unit	CXC2200
	23	Arm Unit	CXC2201
	24	Motor Unit(M571)	CXC2204
	25	Holder	CNC8659
	26	Gear Unit	CXC2205
	27	Chassis Unit	See Contrast table(2)
	28	Screw	JFZ20P025FTC
	29	Washer	YE15FTC
	30	Detach Grille Assy	See Contrast table(2)
	31	Screw	BPZ20P090FZK
	32	Button(OPEN)	CAC8459
	33	Button(RESET)	CAC8461
	34	Button(1-6)	CAC8919
	35	Spring	CBH2543
	36	Holder	CND2039
	37	Arm	CNV6963
	38	Lighting Conductor	CNV7974
	39	Lighting Conductor	CNV7975
	40	Keyboard Unit	CWM9270
	41	Flat Cable	CDE7591
	42	Jack(CN1902)	CKN1016
	43	Connector(CN1802)	CKS4792
	44	Connector(CN1903)	CKS4795
	45	Holder	CND1971
	46	Sheet	CNM8658
	47	Sheet	CNM9192
	48	OEL Module	MXK8200
	49	Button Unit(EQ)	CXC2684
	50	Button Unit(BAND/ESC)	CXC2685
	51	Cover Unit	CXC2997
	52	Knob Unit	CXC3698
	53	Knob Unit	CXC3699
	54	Panel	CNS7795
	55	Sub Grille Assy	See Contrast table(2)
	56	Panel Unit	CXC2603
	57	Remote Control Unit	CXC2665
	58	Cover	CZN5357
	59	Screw(M2x2)	CBA1561
	60	Screw(M2x2)	CBA1633
	61	Screw(M2x3.5)	CBA1754
	62	Spring	CBH2530
	63	Connector	CKS4796
	64	Holder	CND2172
	65	Flexible PCB	CNP7698
	66	Arm	CNV6962
	67	Guide	CNV6967
	68	Guide	CNV8048
	69	Case Unit	CXC2202

(2) CONTRAST TABLE

DEH-P860MP/XN/UC DEH-P8600MP/XN/UC, and DEH-P8650MP/XN/ES are constructed the same except for the following:

Mark	NO	Description	DEH-P860MP/XN/UC	DEH-P8600MP/XN/UC	DEH-P8650MP/XN/ES
	3	Drive Unit	CXC3136	CXC3135	CXC3015
	27	Chassis Unit	CXC3134	CXC3133	CXC2998
	30	Detach Grille Assy	CXC2569	CXC2570	CXC2571
	55	Sub Grille Assy	CXC3738	CXC3737	CXC3736

2.4 EXTERIOR(2)



(1) EXTERIOR(2) SECTION PARTS LIST

Mark	No.	Description	Part No.
	1	Screw	BMZ26P060FZK
	2	Screw	BSZ26P060FTC
	3	Screw(M2.6x14)	CBA1632
	4	IC(IC301)	PAL007A
	5	Transistor(Q742,861,871)	2SD2396
	6	Cord Assy	CDE7701
	7	Fuse(10A)	CEK1136
	8	•••••	
	9	Cap	CNS1472
	10	Cord Assy	See Contrast table(2)
	11	Flat Cable	CDE7468
	12	•••••	
	13	Cord Assy	CDE7626
	14	Earth Plate	CND2171
	15	Insulator	CNM8659
	16	Insulator	CNM8790
	17	Cushion	CNM9126
	18	FM/AM Tuner Unit	CWE1646
	19	Tuner Amp Unit	See Contrast table(2)
	20	Screw	BMZ26P200FTC
	21	Screw	BSZ26P080FTC
	22	Antenna Cable(CN402)	CDH1336
	23	Clamper	CEF1033
	24	Plug(CN932)	CKM1278
	25	Connector(CN351)	CKM1389
	26	Plug(CN571)	CKS-786
	27	•••••	
	28	Connector(CN702)	CKS3126
	29	Connector(CN101)	CKS3408
	30	Connector(CN701)	CKS3837
	31	Connector(CN931)	See Contrast table(2)
	32	Connector(CN561)	CKS4571
	33	Connector(CN801)	CKS4811
	34	Holder(CN401)	CNC5399
	35	Holder	CND2040
	36	Holder	CND2041
	37	Holder	CND1054
	38	Heat Sink	CNR1729
	39	Cap	CNV6727
	40	Resistor	RS1/2PMF102J
	41	Case Unit	CXC3476
	42	CD Mechanism Module(S10CODE)	CXK5677
	43	Screw	ISS26P055FTC
	44	•••••	
	45	Fan Motor(M561)	CXM1288
	46	Sheet	CNM8789

(2) CONTRAST TABLE

DEH-P860MP/XN/UC DEH-P8600MP/XN/UC, and DEH-P8650MP/XN/ES are constructed the same except for the following:

Mark	NO	Description	DEH-P860MP/XN/UC	DEH-P8600MP/XN/UC	DEH-P8650MP/XN/ES
	10	Cord Assy	CDE7436	CDE7437	CDE7436
	19	Tuner Amp Unit	CWM9266	CWM9267	CWM9268
	31	Connector(CN931)	CKS4124	CKS4124	Not used

2.5 CD MECHANISM MODULE



Mark	No.	Description	Part No.
	1	CD Core Unit(S10WMACODE2)	CWX2953
	2	Connector(CN101)	CKS4182
	3	Connector(CN901)	CKS4017
	4	Screw	BMZ20P035FTC
	5	Screw	BSZ20P040FTC
	6	Screw(M2x4)	CBA1362
	7	Screw(M2x3)	CBA1511
	8	Screw(M2x3)	CBA1527
	9	•••••	
	10	Washer	CBF1038
	11	Washer	CBF1060
	12	Spring	CBH2390
	13	Spring	CBH2606
	14	Spring	CBH2607
	15	Spring	CBH2608
	16	Spring	CBH2609
	17	Spring	CBH2610
	18	Spring	CBH2735
	19	Spring	CBH2612
	20	Spring	CBH2613
	21	Spring	CBH2614
	22	Spring	CBH2615
	23	Spring	CBH2616
	24	Spring	CBH2617
	25	Spring	CBH2620
	26	Spring	CBH2621
	27	Spring	CBH2641
	28	Spring	CBH2642
	29	Spring	CBH2643
	30	Spring	CBH2659
	31	Spring	CBH2688
	32	•••••	
	33	Shaft	CLA4441
	34	Frame	CNC9962
	35	Frame	CNC9963
	36	Bracket	CNC9966
	37	Bracket	CND1895
	38	Arm	CNC9968
	39	Arm	CND1909
	40	Lever	CND2032
	41	Lever	CNC9984
	42	Sheet	CNM8134
	43	Collar	CNV7798
	44	Guide	CNV7799
	45	Arm	CNV7800
	46	Rack	CNV7199
	47	Holder	CNV7201
	48	Holder	CNV7202
	49	Arm	CNV7203
	50	Gear	CNV7207
	51	Gear	CNV7208
	52	Gear	CNV7209
	53	Gear	CNV7210
	54	Gear	CNV7211
	55	Gear	CNV7212
	56	Rack	CNV7214
	57	Arm	CNV7215
	58	Arm	CNV7216
	59	Guide	CNV7217
	60	Roller	CNV7218
	61	Gear	CNV7219
	62	Arm	CNV7221
	63	Arm	CNV7220
	64	Arm	CNV7222
	65	Damper	CNV7313
	66	Damper	CNV7314
	67	Arm	CNV7341
	68	Arm	CNV7342
	69	Guide	CNV7360
	70	Guide	CNV7361
	71	Holder	CNV7437
	72	Arm	CNV7805
	73	Gear	CNV7595
	74	Damper	CNV7618
	75	Motor Unit(M1)	CXB6007
	76	Chassis Unit	CXC2318
	77	Screw Unit	CXB8729
	78	Gear Unit	CXC2397
	79	Arm Unit	CXC2316
	80	Arm	CND1896
	81	Arm	CND1894
	82	Motor Unit(M2)	CXB8933
	83	Bracket	CNC9985
	84	•••••	
	85	Screw(M2x5)	EBA1028
	86	Screw	JFZ20P020FTC
	87	Screw	JGZ17P022FTC
	88	•••••	
	89	Washer	YE20FTC
	90	Pickup Unit(P9.9MP3)(Service)	CXX1805
	91	Screw	IMS26P030FTC
	92	Spring	CBL1635
	93	Clamper	CNV7197
	94	Connector(CN902)	CKS2193

3. BLOCK DIAGRAM AND SCHEMATIC DIAGRAM

3.1 BLOCK DIAGRAM




CN101
Q101
B.UP
IP-BUS DRIVER
IC 101
HA12240FP
BUS-
BUS+
RESET
Q651
IC 651
S-80835CNMC-B8U
VDD
RST1
SYSTEM CONTROLLER
IC 601(1/2)
PD5928A
ASENBO
RESET
TX
RX
IPPW
TUNPCE2
TUNPCE1
TUNPDI
TUNPDO
TUNPCK
SL
PEE
DSPMOD
ISENS
TELIN
DALMON
BSENS
ASENS
RQ,DSPCK,
DSPOUT,DSPCS
BZ601
BUZZER
MODE S551
STD
NW
A,C
SWL
RL
FL
IC 321
PA2028A
MUTE
Q352
Q353
Q354
Q351
CN351
SUB WOOFER L
REAR L
FRONT L
FU351
3A
VDD REGULATOR
Q881
Q882
CN932
BACKUP SENSE
Q911
ACC SENSE
BACK UP
ACC
ILM SENSE
Q891
Q921
TELEPHONE MUTE
ILL
TEL MUTE
FUSE
10A
1K(1/2W)
3V→5V
IC 662
TC74VHC08FT
DRDY,RDY,
DSPIN
DRDY3,RDY3,
DSPSO3
5V→3V
IC 661
TC74VHC08FT
RQ3,DSPCK3,
DSPOUT3,DSPCS3
MCKRQ
IC 122
TC7SH08FU
DSP
IC 121
AK7730VT
DOUT,LRCK,BCK
TUN L
BUSL-
BUSL+
SW,LRCKO,
BCKO
DAC
F,LRCKO,
R,LRCKO,
IC 261
NJM2112V
IC 183
IC 213
IC 181
IC 211
LPF
IC 182
IC181-183
:PCM1742KE
IC 212
IC211-213
:NJM4580V
X121
DSPOUT,DSPCK,EVOLCS
IC 281 PML011A
SOURCE SELECTOR
ELECTRONIC VOLUME
Q281
1/2VCC REGULATOR
IC262 NJM4558MD
AUDIO 3V REGULATOR
IC 941
NJM2391DL1-33
AUDIO 8V
D3V
A3V
GND
POWER AMP
IC 301
PAL007A
FLIN
RLIN
MUTE
STBY
B.REMOTE
B.REM
Q301
AUDIO 8V REGULATOR
Q861
Q862
TUN8V
Q871
Q872
Q873
Q451
SYSPW
DSPPW
DAC 5V REGULATOR
IC 961
NJM2872F05
DAC5V
KEYAD
KEYD
A,B
AUTO-EQ
Q501
Q502
AUTOEQ
AEQMIC
Q851
CN931
WIRED REMOTE CONTROL
A:DEH-P860MP/XN/UC
B:DEH-P8600MP/XN/UC
C:DEH-P8650MP/XN/ES
C KEYBOARD UNIT
CN801
CN1903
S1912
SOURCE/VOLUME
ILLUMINATION
ILM+B
Q852
Q853
FLASH MEMORY
IC 1807
PD6468A
Q1806
SWVDD
3.3V REGULATOR
IC 1802
S-818A33AUC-BGN
FONT ROM
IC 1806
PD8124A
IC 1808
TC7WH32FK
KEY MATRIX
KEY DATA
CONTROLLER
601(2/2)
D5928A
Q831
Q832
IC 1901
RS-140
REMOTE CONTROL SENSOR
OPT IN
OEL CONTROLLER/
KEY CONTROLLER
IC 1805
PD5943A
X1801
XIN
XOUT
Q841
Q842
OELPW
OELB
OEL+B
IC 801(1/2)
TC74VHCT125AFT
GDTC1
GDTC2
DPDT
RST
RST1
S1909
RESET
Q1906
S1913
MULTI CONTROL
CN1802
OEL MODULE
CKD,LS,D0_L,D1_L,
CD_DATA,CKC
CN1902
MICROPHONE INPUT
AEQGND
KYDT

3.2 OVERALL CONNECTION DIAGRAM(GUIDE PAGE)

Note: When ordering service parts, be sure to refer to " EXPLODED VIEWS AND PARTS LIST" or "ELECTRICAL PARTS LIST".



A-a



A-b


NOTE :
Symbol indicates a resistor.
No differentiation is made between chip resistors and discrete resistors.
Symbol indicates a capacitor.
No differentiation is made between chip capacitors and discrete capacitors.
Decimal points for resistor and capacitor fixed values are expressed as :
2.2→2R2
0.022→R022
AUDIO 3V
DAC5V
HI-OUT
E-VOL
RCA
LPF
BUFFER
RESET
AMP
POWER AMP IC
TUNBV
MUTE
ASL
DELAY
SWVDD
IL+B
TEL IN
WIRED REMOTE
ISENS
VDD
AUDIO8V
B-UP
IC601
PD5928A
CN351
RCA OUT
SUBWOOFER R CH
SUBWOOFER L CH
REAR R CH
REAR L CH
FRONT R CH
FRONT L CH
CN932
CN931
WIRED REMOTE CONTROL
CN1903
CN801
A DEH-P860MP/XN/UC
B DEH-P8600MP/XN/UC
C DEH-P8650MP/XN/ES
The ⚠ mark found on some component parts indicates the importance of the safety factor of the part.
Therefore, when replacing, be sure to use parts of identical designation.


A-b
A-a
A-a A-b
A TUNER AMP UNIT
: SIGNAL LINE
: POWER SUPPLY LINE
DSP
DAC
SYS. MICRO
FAN
M561
FAN MOTOR
CXM1288
CN561
IP-BUS
CN101
3WAY NET
MECHA VD
3V→5V
5V→3V


IC601
PD5928A
CN1903
CN801
CN571
CN702
CN902
CN901
CN701
CN402
CN401
SWITCH UNIT
FLAP MOTOR
CXC2204
TUNER
FM/AM TUNER UNIT
ANTENNA CABLE
MECHA
DSP
AUTO EQ
GRILL
3WAY NET
A-b
A-a
B
C
D



DEH-P860MP/XN/UC



A	DEH-P860MP/XN/UC
B	DEH-P8600MP/XN/UC
C	DEH-P8650MP/XN/ES

The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.

3.3 KEYBOARD UNIT



C KEYBOARD UNIT



3.4 CD MECHANISM MODULE(GUIDE PAGE)

D-a



D-b

D CD CORE UNIT(S10WMACODE2)




D-b
D-a
IC201
UPD63761GJ
RF AMP, CD DECODER, MP3 AND WMA
DIGITAL SERVO/DATA PROCESSOR
CN101
PICKUP UNIT(P9.9MP3)(SERVICE)
HOLOGRAM UNIT
E:P5+P10
F:P1+P6
F. ACT : Applying positive voltage to FOP.
the lens moves DISC side.
T. ACT : Applying positive voltage to TOP.
the lens moves outer circumference.


D-b
D-a
CD DRIVER
3.3V REGULATOR
M1
CXB6007
SPINDLE MOTOR
M2
CXB8933
LOADING/CARRIAGE
MOTOR
MOTOR DRIVER LOGIC TABLE
LOAD
EJ
PLAY
OFF
CLCONT
LOEJ
CONT
4.00MHz
Pull-down
manual soldering points

D CD CORE UNIT(S10WMACODE2)



NOTE1) GND ...CD LSI, RFAMP, CPU
PGND ...Actuator, Motor Driver
AGND ...Audio
These GND's are not connected to each other on PCB.
PGND is connected to a floating mechanism part by a screw.

SWITCHES:
CD CORE UNIT(S10WMACODE2)
S901 : HOME SWITCH.....ON-OFF
S902 : CLAMP SWITCH.....ON-OFF
S903 : DSCSNS SWITCH.....ON-OFF
S904 : 12EJ SWITCH.....ON-OFF
S905 : 8EJ SWITCH.....ON-OFF
The underlined indicates the switch position.

SIGNAL LINE
F FOCUS SERVO LINE
T TRACKING SERVO LINE
C CARRIAGE SERVO LINE
S SPINDLE SERVO LINE

DEH-P860MP/XN/UC
1GJ

A
CN701
CN901
CD3VON
VD2
VD
VDD
BRST
BRXEN
BSRQ
LRCKOK
LRCK
BCK
DOUT
EMPH
CSENS
RESET
VDOUT
BDATA
BSCK
VDCONT
GND
PGND
1/0
3.3V REGULATOR
A
CN702
MCK
MCKGND
RX
TX
MICRO COMPUTER
IC701
PE5423A
3VDD
GND
XINT
XWRITE
XREAD
D-a
D-b
2
3
4
5
D-b
DEH-P860MP/XN/UC
33

● Waveforms

Note : 1. The encircled numbers denote measuring points in the circuit diagram.
2. Reference voltage REFO1(1.65V)

① DSCSNS 5V/div 500ms/div ② 8SNS 5V/div ③ 12SNS 5V/div ④ LOEJ 5V/div 12 cm CD Loading operation  	① DSCSNS 5V/div 500ms/div ⑤ CLCONT 5V/div ④ LOEJ 5V/div ⑥ VD 10V/div 12 cm CD Loading operation  	① DSCSNS 5V/div 500ms/div ② 8SNS 5V/div ③ 12SNS 5V/div ④ LOEJ 5V/div 8 cm CD Loading operation 
⑦ SIN 1V/div 2s/div ⑧ CIN 500mV/div ⑨ TIN 500mV/div 12 cm CD-DA setup operation after loading  	⑦ SIN 1V/div 1s/div ⑧ CIN 500mV/div ⑨ TIN 500mV/div 12 cm CD-ROM(1 session) setup operation after loading  	⑦ SIN 1V/div 2s/div ⑧ CIN 500mV/div ⑨ TIN 500mV/div 12 cm CD-ROM(3 sessions) setup operation after loading 
⑩ FIN 200mV/div 500ms/div ⑪ RFOK 2V/div ⑦ SIN 2V/div 12 cm CD-DA Source On setup operation  	⑫ TE 500mV/div 200ms/div ⑬ FE 500mV/div Source On setup operation  	⑬ FE 500mV/div 20ms/div ⑩ FIN 500mV/div ⑫ TE 500mV/div ⑨ TIN 500mV/div CD-DA Play operation 
⑬ FE 500mV/div 20ms/div ⑩ FIN 500mV/div ⑫ TE 500mV/div ⑨ TIN 500mV/div CD-ROM play operation(Regular track Jump)  	⑭ MDX 1V/div 50ms/div ⑦ SIN 200mV/div Spindle waveform during play operation  	⑭ MDX 2V/div 5µs/div ⑦ SIN 1V/div Spindle waveform during play operation (Wider) 

⑩ FIN 500mV/div 200ms/div
⑬ FE 500mV/div

Focus Search waveform



⑫ TE 500mV/div 2ms/div
⑮ RFAGC 500mV/div

Track Open waveform



⑮ RFAGC 1V/div 500µs/div
⑫ TE 500mV/div
⑨ TIN 500mV/div

1 Track Jump waveform



⑮ RFAGC 1V/div 500µs/div
⑫ TE 500mV/div
⑨ TIN 500mV/div

4 Tracks Jump waveform



⑮ RFAGC 1V/div 1ms/div
⑫ TE 500mV/div
⑨ TIN 500mV/div

10 Tracks Jump waveform



⑮ RFAGC 1V/div 2ms/div
⑫ TE 500mV/div
⑨ TIN 500mV/div

32 Tracks Jump waveform



① DSCSNS 5V/div 500ms/div
② 8SNS 5V/div
③ 12SNS 5V/div
④ LOEJ 5V/div

12 cm CD Eject operation



① DSCSNS 5V/div 500ms/div
⑤ CLCONT 5V/div
④ LOEJ 5V/div

12 cm CD Eject operation



① DSCSNS 5V/div 500ms/div
② 8SNS 5V/div
③ 12SNS 5V/div
④ LOEJ 5V/div

8 cm CD Eject operation



⑮ RFAGC 1V/div 200ms/div
⑫ TE 1V/div
⑧ CIN 500mV/div
⑦ SIN 2V/div

Search operation(Outter to Inner)



⑦ SIN 1V/div 500ms/div
⑧ CIN 500mV/div
⑨ TIN 500mV/div

CD-ROM >> CD-DA mode change(Band key)



⑦ SIN 1V/div 500ms/div
⑧ CIN 500mV/div
⑨ TIN 500mV/div

CD-DA >> CD-ROM mode change(Band key)



⑯ LRCK 2V/div ⑰ BCK 2V/div ⑱ DOUT 2V/div	⑯ LRCK 1V/div ⑰ BCK 1V/div	⑯ LRCK 1V/div ⑱ DOUT 1V/div
5µs/div	1µs/div	1µs/div
Digtal audio waveform Ref.: GND Mode: Normal 	Digtal audio waveform Ref.: GND Mode: Normal 	Analog audio waveform Ref.: AGND Mode: Normal 

A

B

C

D

E

F

4. PCB CONNECTION DIAGRAM
4.1 TUNER AMP UNIT

NOTE FOR PCB DIAGRAMS

1. The parts mounted on this PCB include all necessary parts for several destination.
   For further information for respective destinations, be sure to check with the schematic diagram.
2. Viewpoint of PCB diagrams






CORD ASSY(RCA OUT)
ANTENNA CABLE
SIDE A
CN402
CN351
IP-BUS
CN101
CN401
IC301
FM/AM TUNER UNIT
CN902
CN901
CN571
M571
FLAP MOTOR
CN702
CN701
FRONT
IC,Q
IC301
Q351 Q352 Q353
Q301
Q354
Q101
Q561
Q281 Q872
IC461 Q871
Q911
Q562
IC281
Q861 IC321
Q402
IC211 IC212 IC213
IC261 Q401
Q882
Q742
IC181 IC182 IC183
IC961 IC122 Q741
IC601 Q744
IC522 VR521
Q853
IC121
Q841
IC521 IC661
Q831
IC641
IC662
IC571 Q651
Q501
IC801 IC651
Q571
Q851

A

A TUNER AMP UNIT



SIDE B


C307
L921
R924
D921
R923
R541
R542
C563
C462
R891
Q891
C891
Q921
R922
R921
Q873
R875
R913
R914
R454
Q451
R452
R453
C872
R872
R873
C282
C281
R281
C270
C153
R271
R273
IC262
R272
R274
C269
R864
R865
Q862
C862
R884
C551
R552
R551
R553
C202
C203
C882
Q881
R881
C702
C701
C148
C156
C147
C130
C742
Q743
C133
C137
R130
C140
L125
C144
C149
C150
C844
R743
C964
C965
C155
C943
C942
R854
R855
Q852
R707
R702
R705
R704
R714
R141
C661
R121
C946
C141
C123
C122
L121
C139
IC941
R833
R832
R831
C842
C816
R841
Q842
R706
R653
R709
R703
R701
R708
R667
R671
R670
R669
R666
R807
L801
C802
C704
R813
R805
R823
R820
R804
R806
R811
C815
D502
R507
C503
C501
R504
R502
R501
Q502
R503
R506
R816
C801
R815
R802
L803
R803
R825
C803
Q832
C831
C948

4.2 SWITCH UNIT

B SWITCH UNIT



4.3 KEYBOARD UNIT

C KEYBOARD UNIT **SIDE A**



C KEYBOARD UNIT **SIDE B**



4.4 CD MECHANISM MODULE

D CD CORE UNIT(S10WMACODE2)

SIDE A



D CD CORE UNIT(S10WMACODE2)

SIDE B



IC, Q

IC203

Q603

Q601

Q701

IC501

D

5. ELECTRICAL PARTS LIST

NOTE:

- *Parts whose parts numbers are omitted are subject to being not supplied.*
- *The part numbers shown below indicate chip components.*

Chip Resistor

RS1/◯S◯◯◯J,RS1/◯◯S◯◯◯J

Chip Capacitor (except for CQS.....)

CKS....., CCS....., CSZS.....

- *The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.*

A

Unit Number:CWM9266(P860MP)
Unit Number:CWM9267(P8600MP)
Unit Number:CWM9268(P8650MP)
Unit Name:Tuner Amp Unit

MISCELLANEOUS

Circuit Symbol and No.		Part No.
IC 101	IC	HA12240FP
IC 121	IC	AK7730VT
IC 122	IC	TC7SH08FU
IC 181	IC	PCM1742KE
IC 182	IC	PCM1742KE
IC 183	IC	PCM1742KE
IC 211	IC	NJM4580V
IC 212	IC	NJM4580V
IC 213	IC	NJM4580V
IC 261	IC	NJM2112V
IC 262	IC	NJM4558MD
IC 281	IC	PML011A
IC 301	IC	PAL007A
IC 321	IC	PA2028A
IC 401	IC	NJM2391DL1-33
IC 521	IC	NJM4558V
IC 522	IC	NJM4558V
IC 571	IC	BA6288FS
IC 601	IC	PD5928A
IC 651	IC	S-80835CNMC-B8U
IC 661	IC	TC74VHC08FT
IC 662	IC	TC74VHC08FT
IC 801	IC	TC74VHCT125AFT
IC 941	IC	NJM2391DL1-33
IC 961	IC	NJM2872F05
Q 101	Transistor	UMF23N
Q 281	Transistor	DTC124EU
Q 301	Transistor	DTC124EU
Q 351	Transistor	IMD2A
Q 352	Transistor	HN1C03F
Q 353	Transistor	HN1C03F
Q 354	Transistor	HN1C03F
Q 451	Transistor	2SC3052-12
Q 501	Transistor	IMD2A
Q 502	Transistor	2SC3052-12
Q 561	Transistor	2SD1859
Q 562	Transistor	IMD2A
Q 571	Transistor	2SD1760F5
Q 572	Transistor	IMD3A
Q 651	Transistor	2SC3052-12
Q 741	Transistor	IMD2A
Q 742	Transistor	2SD2396
Q 743	Transistor	2SD1767
Q 744	Transistor	IMD2A
Q 831	Transistor	2SB808
Q 832	Transistor	DTC114EU
Q 841	Transistor	2SD1760F5
Q 842	Transistor	IMD2A
Q 851	Transistor	2SC3052-12
Q 852	Transistor	2SD1767
Q 853	Transistor	IMD2A
Q 861	Transistor	2SD2396
Q 862	Transistor	IMD2A
Q 871	Transistor	2SD2396
Q 872	Transistor	2SB1243
Q 873	Transistor	RT1N141C-12
Q 881	Transistor	2SD1760F5
Q 882	Transistor	IMD2A
Q 891	Transistor	DTC114EU
Q 911	Transistor	IMX1
Q 921	Transistor	2SA1235A-12
D 301	Diode	MPG06G-6415G50
D 302	Diode	MPG06G-6415G50
D 321	Diode (P860MP,P8650MP)	1SS396
	Diode (P8600MP)	DA204K
D 322	Diode (P860MP,P8650MP)	1SS396
D 351	Diode	1SS133
D 401	Diode	1SR154-400
D 402	Diode	1SR154-400
D 403	Diode	1SR154-400
D 451	Diode	DAN202U
D 452	Diode	HZS9L(A2)
D 501	Diode	HZU3R9(B1)
D 502	Diode Network	DA204U
D 521	Diode	UDZS3R9(B)
D 522	Diode	RB706F-40
D 561	Diode	HZS11L(B2)
D 571	Diode	1SS133
D 572	Diode	1SS133
D 573	Diode	HZS7L(B3)
D 651	Diode	MA111

Circuit Symbol and No.		Part No.
D 741	Diode	HZS9L(B1)
D 742	Diode	HZS6L(C1)
D 801	Diode Network	DA204U
D 802	Diode Network	DA204U
D 803	Diode Network	DA204U
D 804	Diode Network	DA204U
D 805	Diode Network	DA204U
D 806	Diode Network	DA204U
D 807	Diode Network	DA204U
D 841	Diode	HZS9L(C2)
D 851	Diode	HZU10(B2)
D 852	LED	SML310BA1T
D 861	Diode	HZS9L(B3)
D 862	Diode	DAN202U
D 871	Diode	HZS9L(B2)
D 881	Diode	HZS6L(B1)
D 882	Diode	MPG06G-6415G50
D 901	Diode	MPG06G-6415G50
D 902	Diode	MPG06G-6415G50
D 903	Diode	MPG06G-6415G50
D 911	Diode	HZS7L(C3)
D 912	Diode	HZS7L(A1)
D 921	Diode	DAN202U
D 931	Diode (P860MP,P8600MP)	DAN202U
D 932	Diode (P860MP,P8600MP)	DAP202U
ZNR401	Surge Protector	RCCA-201Q31UA-PI
L 101	Inductor	LCTC4R7K2125
L 121	Inductor	LCTA1R0J2520
L 122	Inductor	LCTA1R0J2520
L 123	Inductor	CTF1379
L 124	Inductor	CTF1379
L 125	Inductor	CTF1389
L 126	Inductor	CTF1379
L 181	Inductor	CTF1379
L 182	Inductor	CTF1379
L 184	Inductor	CTF1379
L 185	Inductor	CTF1379
L 186	Inductor	CTF1379
L 187	Inductor	CTF1379
L 281	Inductor	LCTA2R2J2520
L 321	Ferri-Inductor	LAU101J
L 401	Inductor	LCTA4R7J2520
L 402	Inductor	LAYU1R0K
L 403	Inductor	LAYU100K
L 404	Inductor	LAYU1R0K
L 602	Inductor	LAYU100K
L 661	Inductor	LCTC4R7K1608
L 662	Inductor	LCTC4R7K1608
L 701	Inductor	LAYU100K
L 801	Inductor	LCTC1R0K1608
L 803	Inductor	CTF1379
L 921	Inductor	CTF1530
L 941	Inductor	LCTA1R0J2520
L 942	Inductor	LCTA1R0J2520
X 121	Radiator 16.934MHz	CSS1620
X 601	Radiator 10.00MHz	CSS1475
S 551	Slide Switch(DSP) (P860MP,P8650MP)	CSH1051
VR521	Semi-fixed 10kΩ(B)	CCP1448
FU351	Fuse 3A ⚠	CEK1286
MIC521	Microphone	CPM1011
BZ601	Buzzer	CPV1062
Y 401	FM/AM Tuner Unit	CWE1646

RESISTORS

R 101	RS1/16S181J
R 102	RS1/16S181J
R 103	RS1/16S223J
R 104	RS1/16S223J
R 105	RS1/16S102J
R 106	RS1/16S102J
R 107	RS1/16S222J
R 108	RS1/16S150J
R 109	RS1/16S470J
R 110	RS1/16S101J
R 111	RS1/16S101J
R 112	RS1/16S102J
R 113	RS1/16S562J
R 114	RS1/16S332J
R 115	RS1/16S472J
R 121	RS1/16S101J
R 123	RAB4C101J
R 126	RAB4C101J
R 130	RAB4C681J
R 134	RS1/16S562J
R 135	RS1/16S472J
R 136	RS1/16S222J
R 141	RAB4C681J
R 181	RAB4C101J
R 184	RS1/16S101J
R 185	RAB4C101J
R 188	RAB4C101J
R 191	RS1/16S101J
R 192	RAB4C101J
R 195	RAB4C101J
R 198	RS1/16S101J
R 199	RAB4C101J
R 211	RN1/16SE1202D
R 212	RN1/16SE1202D
R 213	RN1/16SE3901D
R 214	RN1/16SE3901D
R 215	RN1/16SE1002D
R 216	RN1/16SE1002D
R 217	RN1/16SE1502D
R 218	RN1/16SE1502D
R 219	RN1/16SE1202D
R 220	RN1/16SE1202D
R 221	RN1/16SE3901D
R 222	RN1/16SE3901D
R 223	RN1/16SE1002D
R 224	RN1/16SE1002D
R 225	RN1/16SE1502D
R 226	RN1/16SE1502D
R 227	RN1/16SE1202D
R 228	RN1/16SE1202D
R 229	RN1/16SE3901D
R 230	RN1/16SE3901D
R 231	RN1/16SE1002D
R 232	RN1/16SE1002D
R 233	RN1/16SE1502D

Circuit Symbol and No.		Part No.
R 234		RN1/16SE1502D
R 261		RN1/16SE3300D
R 262		RN1/16SE3300D
R 263		RN1/16SE3300D
R 264		RN1/16SE3300D
R 265		RN1/16SE4702D
R 266		RN1/16SE4702D
R 267		RN1/16SE4702D
R 268		RN1/16SE4702D
R 269		RN1/16SE4702D
R 270		RN1/16SE4702D
R 271		RS1/16S563J
R 272		RS1/16S473J
R 273		RS1/16S473J
R 274		RS1/16S473J
R 275		RN1/16SE4702D
R 276		RN1/16SE4702D
R 282		RS1/16S682J
R 283		RS1/16S0R0J
R 284		RS1/16S0R0J
R 285		RS1/16S0R0J
R 286		RS1/16S0R0J
R 287		RS1/16S0R0J
R 288		RS1/16S0R0J
R 289		RS1/16S103J
R 290		RS1/16S222J
R 291		RS1/16S332J
R 301		RS1/16S103J
R 302		RS1/16S103J
R 303		RS1/16S103J
R 304		RS1/16S331J
R 321		RS1/16S103J
R 322		RS1/16S103J
R 329	(P8600MP)	RS1/16S0R0J
R 351		RS1/16S820J
R 352		RS1/16S820J
R 353		RS1/16S103J
R 354		RS1/16S103J
R 355		RS1/16S223J
R 356		RS1/16S223J
R 357		RS1/16S471J
R 358		RS1/16S471J
R 359		RS1/16S820J
R 360		RS1/16S820J
R 361		RS1/16S103J
R 362		RS1/16S103J
R 363		RS1/16S223J
R 364		RS1/16S223J
R 365		RS1/16S471J
R 366		RS1/16S471J
R 367		RS1/16S820J
R 368		RS1/16S820J
R 369		RS1/16S103J
R 370		RS1/16S103J
R 371		RS1/16S223J
R 372		RS1/16S223J
R 373		RS1/16S471J
R 374		RS1/16S471J
R 375		RS1/16S102J
R 401		RS1/16S681J

Circuit Symbol and No.		Part No.
R 402		RS1/16S681J
R 403		RS1/16S681J
R 404		RS1/16S681J
R 405		RS1/16S681J
R 406		RS1/16S681J
R 452		RS1/16S103J
R 453		RS1/16S223J
R 454		RS1/16S473J
R 501		RS1/16S682J
R 502		RS1/16S152J
R 503		RS1/16S683J
R 504		RS1/16S153J
R 505		RS1/16S561J
R 506		RS1/16S222J
R 507		RS1/16S104J
R 521		RS1/16S103J
R 522		RS1/16S153J
R 523		RS1/16S153J
R 524		RS1/16S103J
R 525		RS1/16S223J
R 526		RS1/16S102J
R 527		RS1/16S563J
R 528		RS1/16S101J
R 529		RS1/16S152J
R 530		RS1/16S152J
R 531		RS1/16S104J
R 532		RS1/16S222J
R 533		RS1/16S104J
R 534		RS1/16S104J
R 551	(P8600MP)	RS1/16S473J
R 552	(P860MP,P8650MP)	RS1/16S0R0J
R 553	(P860MP,P8650MP)	RS1/16S473J
R 561		RS1/16S1R0J
R 562		RS1/16S391J
R 571		RS1/16S102J
R 572		RS1/16S102J
R 573		RS1/16S102J
R 574		RS1/16S102J
R 575		RS1/16S471J
R 576		RS1/16S471J
R 601		RS1/16S104J
R 602		RS1/16S472J
R 603		RS1/16S104J
R 604		RS1/16S104J
R 605		RS1/16S104J
R 606		RS1/16S223J
R 607		RS1/16S104J
R 608		RS1/16S473J
R 609		RS1/16S0R0J
R 612		RS1/16S104J
R 613		RS1/16S104J
R 614		RS1/16S681J
R 615		RS1/16S681J
R 616		RS1/16S681J
R 617		RS1/16S473J
R 618	(P8600MP)	RS1/16S104J
R 619	(P860MP,P8650MP)	RS1/16S104J
R 621	(P8650MP)	RS1/16S104J
R 622		RS1/16S102J
R 626	(P860MP,P8600MP)	RS1/16S104J

Circuit Symbol and No.		Part No.
R 642		RS1/16S104J
R 651		RS1/16S102J
R 652		RS1/16S222J
R 653		RS1/16S102J
R 654		RS1/16S473J
R 655		RS1/16S183J
R 661		RAB4C681J
R 662		RS1/16S681J
R 663		RS1/16S681J
R 665		RS1/16S681J
R 666		RS1/16S272J
R 667		RS1/16S272J
R 668		RS1/16S272J
R 669		RS1/16S472J
R 670		RS1/16S472J
R 671		RS1/16S472J
R 701		RS1/16S682J
R 702		RS1/16S473J
R 703		RS1/16S682J
R 704		RS1/16S682J
R 705		RS1/16S682J
R 707		RS1/16S681J
R 708		RS1/16S221J
R 709		RS1/16S221J
R 710		RS1/16S221J
R 711		RS1/16S221J
R 712		RS1/16S221J
R 713		RS1/16S221J
R 714		RS1/16S681J
R 741		RD1/4PU331J
R 743		RS1/16S471J
R 801		RS1/16S104J
R 802		RS1/16S104J
R 803		RS1/16S104J
R 804		RS1/16S222J
R 805		RS1/16S222J
R 806		RS1/16S222J
R 811		RS1/16S222J
R 813		RS1/16S222J
R 815		RS1/16S104J
R 816		RS1/16S104J
R 820		RS1/16S222J
R 823		RS1/16S222J
R 825		RS1/16S473J
R 831		RS1/16S473J
R 832		RS1/16S222J
R 833		RS1/16S103J
R 841		RS1/10S1R0J
R 843		RD1/4PU271J
R 851		RAB4C221J
R 852		RS1/16S103J
R 853		RS1/16S103J
R 854		RS1/16S181J
R 855		RS1/16S181J
R 864		RS1/16S561J
R 865		RS1/16S561J
R 872		RS1/16S681J
R 873		RS1/16S561J
R 874		RD1/4PU222J
R 875		RS1/16S822J

Circuit Symbol and No.		Part No.
R 881		RS1/16S333J
R 882		RS1/16S821J
R 883		RS1/16S821J
R 891		RS1/16S103J
R 892		RS1/16S104J
R 911		RS1/16S104J
R 912		RS1/16S103J
R 913		RS1/16S473J
R 914		RS1/16S473J
R 915		RS1/16S472J
R 921		RS1/16S102J
R 922		RS1/16S472J
R 923		RS1/16S472J
R 924		RS1/16S153J
R 931		RS1/16S103J
R 932		RS1/16S104J
R 933	(P860MP,P8600MP)	RS1/16S102J
R 934	(P860MP,P8600MP)	RS1/16S102J

CAPACITORS

C 101		CKSRYB104K16
C 103		CCSRCH102J50
C 104		CCSRCH102J50
C 105		CKSRYB473K50
C 121		CKSRYB104K16
C 122		CKSYB106K6R3
C 123		CKSRYB104K16
C 124		CKSYB106K6R3
C 125		CKSRYB104K16
C 126		CKSRYB104K16
C 127		CKSRYB104K16
C 128		CKSYB106K6R3
C 131		CCSRCH220J50
C 132		CKSQYB682K50
C 133		CCSRCH220J50
C 134		CKSRYB104K16
C 135		CCSRCH100D50
C 136		CCSRCH100D50
C 137		CCSRCH220J50
C 138		CKSYB106K6R3
C 139		CCSRCH102J50
C 140		CCSRCH151J50
C 141		CCSRCH102J50
C 142		CKSRYB103K50
C 143		CCSRCH102J50
C 144		CCSRCH390J50
C 146		CCSRCH220J50
C 147		CCSRCH220J50
C 148		CCSRCH220J50
C 150		CCSRCH150J50
C 153		CKSRYB102K50
C 156		CCSRCH102J50
C 183		CKSYB106K6R3
C 184		CCSRCH102J50
C 185		CKSYB106K6R3
C 186		CCSRCH102J50
C 187		CKSYB106K6R3
C 189		CCSRCH102J50
C 190		CKSYB106K6R3
C 192		CKSYB106K6R3

Circuit Symbol and No.	Part No.	Circuit Symbol and No.	Part No.
C 193	CCSRCH102J50	C 294	CKSRYB104K16
C 194	CKSYB106K6R3	C 301	CFTNA224J50
C 196	CCSRCH102J50	C 302	CFTNA224J50
C 197	CKSYB106K6R3	C 303	CFTNA224J50
C 199	CKSYB106K6R3	C 304	CFTNA224J50
C 200	CCSRCH102J50	C 305	CEHAR330M10
C 201	CKSYB106K6R3	C 306 3300µF/16V	CCH1486
C 202	CCSRCH101J50	C 307	CKSRYB104K16
C 211	CEAL4R7M16	C 308	CEHAR100M16
C 212	CEAL4R7M16	C 309	CKSQYB225K10
C 213	CCSRCH181J50	C 310	CKSQYB225K10
C 214	CCSRCH181J50	C 321	CKSRYB105K10
C 215	CCSRCH821J50	C 322	CKSRYB105K10
C 216	CCSRCH821J50	C 323	CKSRYB105K10
C 217	CEALNP4R7M16	C 324	CKSRYB105K10
C 218	CEALNP4R7M16	C 325	CKSRYB105K10
C 219	CEAL4R7M16	C 326	CKSRYB105K10
C 220	CEAL4R7M16	C 327	CEJQ4R7M35
C 221	CCSRCH181J50	C 328	CEJQ101M16
C 222	CCSRCH181J50	C 329	CASAQ3R3M16
C 223	CCSRCH821J50	C 330	CEJQ100M16
C 224	CCSRCH821J50	C 331	CKSYB684K16
C 225	CEALNP4R7M16	C 332	CEJQ220M16
C 226	CEALNP4R7M16	C 333	CKSRYB105K10
C 227	CEAL4R7M16	C 334	CEJQ330M25
C 228	CEAL4R7M16	C 335	CEJQ330M25
C 229	CCSRCH181J50	C 336 (P860MP,P8650MP)	CEJQ330M25
C 230	CCSRCH181J50	C 337 (P860MP,P8650MP)	CEJQ330M25
C 231	CCSRCH821J50	C 351	CEJQ100M50
C 232	CCSRCH821J50	C 352	CEJQ100M50
C 233	CEALNP4R7M16	C 353	CKSRYB222K50
C 234	CEALNP4R7M16	C 354	CKSRYB222K50
C 235	CKSRYB104K16	C 355	CEJQ100M50
C 236	CKSRYB104K16	C 356	CEJQ100M50
C 237	CKSRYB104K16	C 357	CKSRYB222K50
C 261	CCSRCH102J50	C 358	CKSRYB222K50
C 262	CCSRCH102J50	C 359	CEJQ100M50
C 263	CCSRCH470J50	C 360	CEJQ100M50
C 264	CCSRCH470J50	C 361	CKSRYB222K50
C 265	CCSRCH470J50	C 362	CKSRYB222K50
C 266	CCSRCH470J50	C 363	CEJQ220M16
C 267	CKSQYB225K10	C 364	CKSRYB473K50
C 268	CKSQYB225K10	C 401	CKSYB475K10
C 269	CKSRYB105K10	C 402	CKSRYB103K50
C 270	CKSRYB104K16	C 403	CEJQ470M6R3
C 271	CSZS100M10	C 404	CKSRYB103K50
C 272	CSZS100M10	C 405	CEJQ101M16
C 281	CKSRYB472K50	C 406	CKSRYB103K50
C 282	CKSRYB472K50	C 407	CEJQ220M6R3
C 283	CSZS100M10	C 408	CCSRCH101J50
C 284	CKSRYB104K16	C 409	CKSRYB103K50
C 285	CKSQYB225K10	C 410	CKSYB475K10
C 286	CKSRYB104K16	C 411	CCSRCH102J50
C 287	CKSQYB225K10	C 501	CKSQYB225K10
C 288	CKSQYB225K10	C 502	CEJQ101M6R3
C 289	CSZS100M10	C 503	CCSRCH681J50
C 290	CKSQYB225K10	C 521	CKSRYB105K10
C 291	CKSRYB105K10	C 522	CEALNP4R7M16
C 292	CKSQYB225K10	C 523	CEALNP4R7M16
C 293	CKSRYB104K16	C 524	CKSRYB105K10

Circuit Symbol and No.		Part No.
C 525		CKSRYB474K10
C 526		CKSRYB104K16
C 527		CCSRCH101J50
C 528		CKSRYB105K10
C 529		CEAL100M16
C 530		CKSRYB105K10
C 531		CKSRYB105K6R3
C 532		CKSRYB105K6R3
C 561		CEJQ100M16
C 562		CKSRYB103K50
C 563		CKSRYB103K50
C 571		CCSRCH101J50
C 572		CCSRCH102J50
C 573		CEJQ220M16
C 574		CCSRCH101J50
C 575		CKSRYB104K16
C 576		CKSRYB224K10
C 601		CCSRCH180J50
C 602		CCSRCH220J50
C 604		CCSRCH470J50
C 605		CEJQ4R7M35
C 606		CKSRYB103K50
C 652		CKSRYB104K16
C 653		CKSRYB105K10
C 661		CKSRYB104K16
C 662		CKSRYB104K16
C 703	470µF/10V	CCH1438
C 741		CKSRYB473K25
C 742		CCSRCH102J50
C 743		CEJQ101M16
C 744		CKSRYB473K25
C 745		CEHAR101M10
C 801		CKSRYB473K25
C 802		CKSRYB103K50
C 803		CKSRYB102K50
C 805		CEJQ101M16
C 815		CKSRYB104K16
C 816		CKSRYB104K16
C 842		CKSRYB103K50
C 843		CEJQ330M16
C 844		CCSRCH101J50
C 851		CKSRYB473K25
C 861		CEJQ221M10
C 862		CKSRYB472K50
C 863		CEJQ2R2M50
C 871		CEJQ221M10
C 872		CKSRYB103K50
C 873		CEJQ101M16
C 881		CEAL470M6R3
C 882		CKSRYB103K50
C 883		CKSRYB472K50
C 884	470µF/16V	CCH1331
C 885	470µF/16V	CCH1331
C 891		CKSRYB105K10
C 911		CKSRYB104K16
C 942		CCSRCH101J50
C 943		CKSRYB102K50
C 944		CEAL101M6R3
C 945		CEAL220M6R3
C 946		CKSRYB105K6R3

Circuit Symbol and No.		Part No.
C 948		CKSRYB104K16
C 949		CKSYB475K10
C 961		CEAL470M6R3
C 962		CKSRYB104K16
C 964		CKSRYB104K16
C 965		CKSYB475K10

B

Unit Number:CWS1389
Unit Name:Switch Unit

S 1	Switch(CLOSE)	CSN1051
S 2	Switch(OPEN)	CSN1052

C

Unit Number:CWM9270
Unit Name:Keyboard Unit

MISCELLANEOUS

IC 1802	IC	S-818A33AUC-BGN
IC 1805	IC	PD5943A
IC 1806	IC	PD8124A
IC 1807	IC	PD6468A
IC 1808	IC	TC7WH32FK
IC 1901	IC	RS-140
Q 1806	Transistor	UMD2N
Q 1906	Transistor	2SC3052-12
D 1803	Diode	1SS355
D 1901	LED	SML310BA1T
D 1902	LED	SML310BA1T
D 1903	LED	SML310BA1T
D 1904	LED	SML310BA1T
D 1905	LED	SML310BA1T
D 1906	LED	SML310BA1T
D 1907	LED	SML310BA1T
D 1908	LED	SML310BA1T
D 1909	LED	SML310BA1T
D 1910	LED	SML310BA1T
D 1911	LED	SML310BA1T
D 1912	LED	SML310BA1T
D 1913	LED	SML310BA1T
D 1914	LED	SML310BA1T
D 1915	LED	SML310BA1T
D 1916	LED	SML310BA1T
D 1917	LED	SML310BA1T
L 1801	Inductor	CTF1530
L 1802	Inductor	CTF1484
L 1803	Inductor	CTF1530
L 1804	Inductor	CTF1399
X 1801	Radiator 10.0MHz	CSS1577
S 1901	Push Switch	CSG1155
S 1902	Push Switch	CSG1155
S 1903	Push Switch	CSG1155
S 1904	Push Switch	CSG1155
S 1905	Push Switch	CSG1155
S 1906	Push Switch	CSG1155
S 1907	Push Switch	CSG1155
S 1908	Push Switch	CSG1155

Circuit Symbol and No.		Part No.
S 1909	Push Switch	CSG1155
S 1910	Push Switch	CSG1155
S 1911	Push Switch	CSG1155
S 1912	Encoder(SOURCE/VOLUME)	CSD1104
S 1913	Switch(MULTI-CONTROL)	CSX1065
S 1914	Push Switch	CSG1155

RESISTORS

R 1807	RS1/16SS222J
R 1808	RS1/16SS222J
R 1809	RS1/16SS101J
R 1810	RS1/16SS101J
R 1811	RS1/16SS473J
R 1812	RS1/16SS104J
R 1815	RS1/16SS101J
R 1816	RS1/16SS101J
R 1817	RS1/16SS101J
R 1818	RS1/16SS101J
R 1819	RAB4CQ101J
R 1820	RS1/16SS222J
R 1821	RS1/16SS154J
R 1822	RS1/16SS473J
R 1824	RS1/16SS473J
R 1825	RS1/16SS473J
R 1826	RS1/16SS473J
R 1827	RS1/16SS473J
R 1828	RS1/16SS473J
R 1829	RS1/16SS473J
R 1830	RS1/16SS473J
R 1831	RS1/16SS102J
R 1832	RS1/16SS0R0J
R 1834	RAB4CQ473J
R 1835	RAB4CQ101J
R 1836	RAB4CQ101J
R 1837	RAB4CQ101J
R 1838	RAB4CQ101J
R 1839	RAB4CQ101J
R 1840	RAB4CQ101J
R 1841	RAB4CQ101J
R 1842	RAB4CQ101J
R 1843	RAB4CQ101J
R 1844	RAB4CQ101J
R 1845	RS1/16SS473J
R 1846	RS1/16SS473J
R 1847	RS1/16SS473J
R 1849	RS1/16SS392J
R 1850	RS1/16SS682J
R 1851	RAB4CQ101J
R 1852	RS1/16SS101J
R 1853	RS1/16SS101J
R 1854	RS1/16SS0R0J
R 1903	RS1/16SS274J
R 1904	RS1/16SS103J
R 1905	RS1/16SS121J
R 1906	RS1/16SS2R2J
R 1916	RS1/16SS104J
R 1917	RS1/16SS223J
R 1918	RS1/16SS103J

Circuit Symbol and No.	Part No.
R 1919	RS1/16S221J
R 1921	RS1/16S221J
R 1923	RS1/16S221J
R 1925	RS1/16S221J
R 1927	RS1/16S821J
R 1929	RS1/16S221J
R 1931	RS1/16S221J
R 1933	RS1/16S221J
R 1935	RS1/16S221J
R 1938	RS1/16SS222J
R 1939	RS1/16SS332J
R 1940	RS1/16SS822J
R 1941	RS1/16SS4702D
R 1942	RS1/16SS102J
R 1943	RS1/16SS102J
R 1945	RS1/16SS103J
R 1946	RS1/16SS221J

CAPACITORS

C 1806		CSZSP4R7M10
C 1808		CKSRYB474K10
C 1809		CKSSYB103K16
C 1810		CKSSYB103K16
C 1814		CKSSYB473K10
C 1816		CKSSYB103K16
C 1817		CSZSP4R7M10
C 1822		CKSSYB103K16
C 1826		CKSSYB103K16
C 1827		CKSSYB103K16
C 1833	10µF	CCG1138
C 1901		CKSRYB104K16
C 1902		CKSRYB104K16
C 1903		CKSRYB104K16
C 1904		CKSRYB104K16
C 1905		CKSRYB104K16
C 1906		CKSRYB104K16
C 1907		CKSRYB104K16
C 1908		CKSRYB104K16
C 1909		CKSRYB104K16
C 1910		CKSRYB104K16
C 1911		CKSRYB104K16
C 1912		CKSRYB104K16
C 1913		CKSRYB104K16
C 1914		CKSRYB104K16
C 1915		CKSRYB104K16
C 1916		CKSRYB104K16
C 1917		CKSRYB104K16
C 1918		CKSSYB104K10
C 1919		CKSSYB104K10
C 1920		CSZSR100M16

D

Unit Number:CWX2953

Unit Name:CD CORE UNIT(S10WMACODE2)

MISCELLANEOUS

IC 201	IC	UPD63761GJ
IC 203	IC	NJM2391DL1-33

Circuit Symbol and No.		Part No.
IC 301	IC	BA5835FM
IC 501	IC	S-L2980A15MC-C6A
IC 701	IC	PE5423A
IC 703	IC	S-812C33AUA-C2N
Q 101	Transistor	2SB1132
Q 701	Transistor	UN2111
D 101	Diode	1SS355
L 203	Inductor	CTF1389
L 207	Inductor	CTF1389
L 209	Inductor	CTF1389
L 703	Inductor	CTF1389
L 902	Inductor	CTF1306
L 903	Inductor	CTF1306
L 904	Inductor	CTF1306
X 702	Resonator 4.00MHz	CSS1654
S 901	Switch(HOME)	CSN1051
S 902	Switch(CLAMP)	CSN1051
S 903	Spring Switch(DSCSNS)	CSN1052
S 904	Switch(12EJ)	CSN1051
S 905	Switch(8EJ)	CSN1051

RESISTORS

R 101	RS1/10S1R5J
R 102	RS1/10S1R5J
R 103	RS1/10S1R5J
R 104	RS1/10S1R5J
R 105	RS1/10S1R5J
R 107	RS1/16SS0R0J
R 201	RS1/16SS102J
R 202	RS1/16SS333J
R 205	RS1/16SS473J
R 207	RS1/16SS473J
R 209	RS1/16SS473J
R 210	RS1/16SS0R0J
R 214	RS1/16SS472J
R 216	RS1/16SS472J
R 218	RS1/16SS472J
R 220	RS1/16SS472J
R 221	RS1/16SS103J
R 222	RS1/16SS103J
R 223	RS1/16SS0R0J
R 224	RS1/16SS0R0J
R 225	RS1/16SS103J
R 226	RS1/16SS393J
R 227	RS1/16SS562J
R 228	RS1/16SS122J
R 229	RS1/16SS472J
R 231	RS1/16SS0R0J
R 232	RS1/16SS122J
R 233	RS1/16SS0R0J
R 237	RS1/16SS221J
R 238	RS1/16SS221J
R 239	RS1/16SS221J
R 240	RS1/16SS0R0J
R 241	RS1/16SS333J
R 243	RS1/16SS333J
R 245	RS1/16SS333J
R 250	RS1/16SS0R0J
R 256	RS1/16SS0R0J

Circuit Symbol and No.	Part No.
R 261	RS1/16S0R0J
R 262	RS1/16S0R0J
R 263	RS1/16S0R0J
R 264	RS1/16S0R0J
R 267	RS1/16S0R0J
R 301	RS1/16SS183J
R 302	RS1/16SS822J
R 304	RS1/16SS183J
R 305	RS1/16SS822J
R 307	RS1/16SS183J
R 308	RS1/16SS183J
R 309	RS1/16SS183J
R 310	RS1/16SS183J
R 501	RS1/16SS0R0J
R 701	RS1/16S0R0J
R 702	RS1/16SS0R0J
R 703	RS1/16SS104J
R 704	RS1/16SS104J
R 705	RS1/16SS221J
R 706	RS1/16SS221J
R 707	RS1/16SS0R0J
R 708	RS1/16SS221J
R 709	RS1/16SS473J
R 710	RS1/16SS102J
R 711	RS1/16SS102J
R 712	RS1/16SS102J
R 713	RS1/16SS102J
R 714	RS1/16SS473J
R 715	RS1/16SS101J
R 716	RS1/16SS472J
R 717	RS1/16SS221J
R 718	RS1/16SS221J
R 719	RS1/16SS221J
R 720	RS1/16SS471J
R 721	RS1/16S0R0J
R 724	RS1/16S473J
R 725	RS1/16SS222J
R 726	RS1/16SS103J
R 727	RS1/16SS473J
R 729	RS1/16SS223J
R 730	RS1/16SS473J
R 731	RS1/16SS104J
R 732	RS1/16SS104J
R 733	RS1/16SS104J
R 735	RS1/16SS473J
R 737	RS1/16SS104J
R 740	RS1/16SS473J
R 743	RS1/16SS104J
R 745	RS1/16SS473J
R 746	RS1/16SS104J
R 747	RS1/16SS102J
R 750	RS1/16SS473J
R 751	RS1/16SS102J
R 754	RS1/16SS102J
R 755	RS1/16SS102J
R 756	RS1/16SS104J
R 765	RAB4CQ221J
R 769	RAB4CQ221J
R 773	RAB4CQ221J
R 777	RS1/16SS221J

Circuit Symbol and No.		Part No.
R 778		RS1/16SS221J
R 779		RS1/16SS221J
R 901		RAB4CQ221J
R 902		RS1/16S0R0J
R 905		RS1/16SS221J
R 906		RS1/16SS221J
R 909		RS1/16SS0R0J
R 911		RS1/16SS0R0J

CAPACITORS

C 101		CKSSYB104K10
C 102		CKSSYB104K10
C 103	100µF/16V	CCH1504
C 104	47µF/6.3V	CCH1506
C 105		CKSSYB104K10
C 106		CCSSCH101J50
C 107		CKSRYB224K16
C 108		CKSSYB104K10
C 110		CKSSYB104K10
C 201		CKSSYB471K50
C 202		CKSSYB104K10
C 203		CKSSYB104K10
C 205		CKSSYB104K10
C 207	220µF/4V	CCH1590
C 208		CKSSYB104K10
C 209		CKSSYB104K10
C 216		CKSSYB332K50
C 217		CKSSYB104K10
C 218		CKSSYB223K16
C 219		CKSSYB104K10
C 220		CKSSYB103K16
C 221		CKSSYB104K10
C 222		CCSSCH560J50
C 223		CCSSCH5R0C50
C 224		CKSSYB104K10
C 225		CKSSYB103K16
C 226		CCSSCH680J50
C 227		CCSSCH470J50
C 228		CKSSYB682K25
C 230		CKSSYB104K10
C 232		CKSSYB104K10
C 233	10µF/6.3V	CCH1470
C 234	220µF/4V	CCH1590
C 235		CKSRYB224K16
C 237		CKSSYB104K10
C 239		CCSSCH330J50
C 242		CKSSYB104K10
C 246		CKSSYB104K10
C 249		CKSSYB221K50
C 250		CKSRYB102K50
C 251		CKSRYB102K50
C 260		CKSSYB104K10
C 301		CKSSYB221K50
C 302		CKSSYB221K50
C 303		CKSSYB472K25
C 304		CKSSYB103K16
C 305	100µF/16V	CCH1504
C 306		CKSSYB104K10
C 307		CKSSYB104K10
C 501		CKSRYB224K16

Circuit Symbol and No.		Part No.
C 505		CKSQYB475K6R3
C 701		CKSSYB104K10
C 702		CKSSYB471K50
C 703		CKSSYB103K16
C 704	4.7µF/25V	CCH1592
C 706		CKSSYB104K10
C 707		CKSSYB104K10
C 712		CKSRYB224K16
C 713		CKSSYB104K10
C 714		CKSSYB104K10
C 716		CKSSYB103K16
C 717		CCSSCH180J50
C 718		CCSSCH180J50
C 720		CKSQYB225K10
C 722		CKSRYB105K10
C 903		CKSSYB471K50
C 906		CKSRYB224K16
C 910		CKSQYB225K10

Miscellaneous Parts List

	Pickup Unit(P9.9MP3)(Service)	CXX1805
M 1	Motor Unit(SPINDLE)	CXB6007
M 2	Motor Unit(LOADING/CARRIAGE)	CXB8933
M 561	Fan Motor	CXM1288
M 571	Motor Unit(FLAP)	CXC2204

6. ADJUSTMENT

6.1 JIG CONNECTION DIAGRAM



6.2 CD ADJUSTMENT

1) Cautions on adjustments

• In this product the single voltage (3.3V) is used for the regulator. The reference voltage is the REFO1 (1.65V) instead of the GND.
If you should mistakenly short the REFO1 with the GND during adjustment, accurate voltage will not be obtained, and the servo's misoperation will apply excessive shock to the pickup. To avoid such problems:
a. Do not mix up the REFO1 with the GND when connecting the (-) probe of measuring instruments. Especially on an oscilloscope, avoid connecting the (-) probe for CH1 to the GND.
b. In many cases, measuring instruments have the same potential as that for the (-) probe. Be sure to set the measuring instruments to the floating state.
c. If you have mistakenly connected the REFO1 to the GND, turn off the regulator or the power immediately.

• Before mounting and removing filters or leads for adjustment, be sure to turn off the regulator.

• For stable circuit operation, keep the mechanism operating for about one minute or more after the regulator is turned on.

• In the test mode, any software protections will not work. Avoid applying any mechanical or electrical shock to the mechanism during adjustment.

• The RFI and RFO signals with a wide frequency range are easy to oscillate. When observing the signals, insert a resistor of 1k ohms in series.

• The load and eject operation is not guarantied with the mechanism upside down. If the mechanism is blocked due to mistaken eject operation, reset the product or turn off and on the ACC to restore it.

2) Test mode

This mode is used to adjust the CD mechanism module.
• To enter the test mode.
While pressing the 4 and 6 keys at the same time, reset.
• To exit from the test mode.
Turn off the ACC and back up.

Notes:
a. During ejection, do not press any other keys than the EJECT key until the loaded disc is ejected.
b. If you have pressed the (→) key or (←) key during focus search, turn off the power immediately to protect the actuator from damage caused by the lens stuck.
c. For the TR jump modes except 100TR, the track jump operation will continue even if the key is released.
d. For the CRG move and 100TR jump modes, the tracking loop will be closed at the same time when the key is released.
e. When the power is turned off and on, the jump mode is reset to the single TR (91), the RF amp gain is set to 0dB, and the auto-adjustment values are reset to the default settings.

● Flow Chart



*1) TYP (TRK MIN SEC) → -6dB (TRK 06 MIN 06 SEC 06) → -12dB (TRK 12 MIN 12 SEC 12)

*2) Focus Close (TRK 00 MIN 00 SEC 00 / TRK 99 MIN 99 SEC 99) → S.Curve ckeck setting (TRK 01 MIN 01 SEC 01) → F EQ measurement setting (TRK 02 MIN 02 SEC 02)

*3) F.Offset Display → T.Offset Display → Switch to the order of the original display

*4) 1TR / 32TR / 100TR

*5) Single TR → 32TR → 100TR → CRG Move
9x(8x) : 91(81) 92(82) 93(83) 94(84)

*6) Only at the time of CRG Move, 100TR Jump

*7) TRK/MIN/SEC → F.AGC → T.AGC → F.Bias → RF AGC

*8) CRG motor voltage = 2[V]

*9) TYP(1X) (TRK MIN SEC) → 2X (TRK 22 MIN 22 SEC 22) → 1X (TRK 11 MIN 11 SEC 11)

As for the double speed (2x), audio output cannot be supported.

TYP(2X) (TRK MIN SEC) → 1X (TRK 11 MIN 11 SEC 11) → 2X (TRK 22 MIN 22 SEC 22)

[Key]	Operation Test Mode
[BAND]	Power On/Off
[→]	CRG + / TR Jump + (Direction of the external surface)
[←]	CRG - / TR Jump - (Direction of the internal surface)
[1]	T.CLS and AGC and Applicable servomechanism / AGC, AGC display switching
[2]	RF Gain switching / Offset adjustment display / T.Balance adjustment / T.Open
[3]	F.Close, S.Curve / Rough Servo and RF AGC / F, T, RF AGC
[4]	SPDL 1X/2X switching As for the double speed (2x), audio output cannot be supported.
[5]	Error Rate measurement 1st-ON : ERR count beginning(30Sec) 2nd-ON : BER display data[%]
[6]	F. Mode switching / Tracking Close / CRG, TR Jump switching

6.3 CHECKING THE GRATING AFTER CHANGING THE PICKUP UNIT

• **Note :**
The grating angle of the PU unit cannot be adjusted after the PU unit is changed. The PU unit in the CD mechanism module is adjusted on the production line to match the CD mechanism module and is thus the best adjusted PU unit for the CD mechanism module. Changing the PU unit is thus best considered as a last resort. However, if the PU unit must be changed, the grating should be checked using the procedure below.

• **Purpose :**
To check that the grating is within an acceptable range when the PU unit is changed.

• **Symptoms of Mal-adjustment :**
If the grating is off by a large amount symptoms such as being unable to close tracking, being unable to perform track search operations, or taking a long time for track searching.

• **Method :**

• Measuring Equipment	• Oscilloscope, Two L.P.F.
• Measuring Points	• E, F, REFO1
• Disc	• TCD-782
• Mode	• TEST MODE

CD CORE UNIT(S10WMACODE2)



• **Checking Procedure**
1. In test mode, load the disc and switch the 3V regulator on.
2. Using the → and ← buttons, move the PU unit to the innermost track.
3. Press key 3 to close focus, the display should read "91". Press key 2 to implement the tracking balance adjustment the display should now read "81". Press key 3. The display will change, returning to "81" on the fourth press.
4. As shown in the diagram above, monitor the LPF outputs using the oscilloscope and check that the phase difference is within 75° . Refer to the photographs supplied to determine the phase angle.
5. If the phase difference is determined to be greater than 75° try changing the PU unit to see if there is any improvement. If, after trying this a number of times, the grating angle does not become less than 75° then the mechanism should be judged to be at fault.

• **Note**
Because of eccentricity in the disc and a slight misalignment of the clamping center the grating waveform may be seen to "wobble" (the phase difference changes as the disc rotates). The angle specified above indicates the average angle.

• **Hint**
Reloading the disc changes the clamp position and may decrease the "wobble".

Grating waveform

Ech → Xch 20mV/div, AC
Fch → Ych 20mV/div, AC

0°



30°



45°



60°



75°



90°



6.4 ERROR MODE

● Error Messages

If a CD is not operative or stopped during operation due to an error, the error mode is turned on and cause(s) of the error is indicated with a corresponding number. This arrangement is intended at reducing nonsense calls from the users and also for facilitating trouble analysis and repair work in servicing.

(1) Basic Indication Method

1) When SERRORM is selected for the CSMOD (CD mode area for the system), error codes are written to DMIN (minutes display area) and DSEC (seconds display area). The same data is written to DMIN and DSEC. DTNO remains in blank as before.

2) Head unit display examples

Depending on display capability of LCD used, display will vary as shown below. xx contains the error number.

8-digit display	6-digit display	4-digit display
ERROR–xx	ERR–xx	E–xx

(2) Error Code List

Code	Class	Displayed error code	Description of the code and potential cause(s)
10	Electricity	Carriage Home NG SERVO LSI Communication Error	CRG can't be moved to inner diameter. CRG can't be moved from inner diameter. → Failure on home switch or CRG move mechanism. Communication error between microcomputer and SERVO LSI.
11	Electricity	Focus Servo NG	Focusing not available. → Stains on rear side of disc or excessive vibrations on REWRITABLE.
12	Electricity	Spindle Lock NG Subcode NG	Spindle not locked. Sub-code is strange (not readable). → Failure on spindle, stains or damages on disc, or excessive vibrations. A disc not containing CD-R data is found. Turned over disc are found, though rarely. CD signal error.
17	Electricity	Setup NG	AGC protection doesn't work. Focus can be easily lost. → Damages or stains on disc, or excessive vibrations on REWRITABLE.
30	Electricity	Search Time Out	Failed to reach target address. → CRG tracking error or damages on disc.
44	Electricity	ALL Skip	Skip setting for all track. (CD-R/RW)
50	Mechanism	CD On Mech Error	Mechanical error during CD ON. → Defective loading motor, mechanical lock and mechanical sensor.
A0	System	Power Supply NG	Power (VD) is ground faulted. → Failure on SW transistor or power supply (failure on connector).

Remarks: Mechanical errors are not displayed (because a CD is turned off in these errors).

Unreadable TOC does not constitute an error. An intended operation continues in this case.

Upper digits of an error code are subdivided as shown below:

1x: Setup relevant errors, 3x: Search relevant errors, Ax: Other errors.

6.5 OEL SCREENSAVER STUDIO LKA TO LKD APPLICATION

"OEL Screensaver Studio" is an application to create OEL display image file. The customer write the image file on a CD-R disc and install it to car audio. This function is similar to PC link-kit (CD-PC1).
"OEL Screensaver Studio" is available to the public on the PIONEER Home Page.
This software (GGV1168) is added LKA to LKD file conversion function to original "OEL Screensaver Studio".

● **How to check:**
1. Set up GGV1168 application.
2. Confirm the LKA file (ent_disp.lka) is converted to LKD file correctly or not.
Please see a Readme.txt in the GGV1168 or help file of "OEL Screensaver Studio" for more information.

6.6 SYSTEM MICROCOMPUTER TEST PROGRAM

● **PCL output**
In the normal operation mode (with the detachable panel installed, the ACC switched ON, the standby mode cancelled), shift the TESTIN (Pin 86) terminal to H.
The clock signal is output from the PCL terminal (Pin 37).
The frequency of the clock signal is 312.500kHz that is one 32nd of the fundamental frequency.
The clock signal should be 312.500kHz ± 13Hz.
If the clock signal is out of the range, the X'tal (X601) should be replaced with new one.

7. GENERAL INFORMATION

7.1 DIAGNOSIS

7.1.1 DISASSEMBLY

● Removing the Case (not shown)

1. Remove the two screws and then remove the Case.

● Removing the CD Mechanism Module (Fig.1)

1 Remove the four screws.

Disconnect the connector and then remove the CD Mechanism Module.



Fig.1

● Removing the Grille Assy (Fig.2)

1 Remove the four screws.

Disconnect the connector and then remove the Grille Assy.



Fig.2

● Removing the Tuner Amp Unit (Fig.3)

1 Remove the three screws.

2 Remove the screw.

3 Straighten the tabs at three locations indicated.

4 Remove the screw and then remove the Tuner Amp Unit.



Fig.3

● Notes when assembling (Fig.4)

1 The Holder hook touches the Sub Grille Assy.

2 The hole Ⓐ of Lighting Conductor is inserted in the portion shown by the arrow of Sub Grille Assy.

3 The hole Ⓑ of Lighting Conductor is inserted in the portion shown by the arrow of Sub Grille Assy.

4 Please do not remove Knob as much as possible from Encoder.



Fig.4

● How to hold the Mechanism Unit

1. Hold the top and bottom frame.
2. Do not squeeze top frame's front portion too tight, because it is fragile.



● Removing the Upper and Lower Frames

1. With a disc clamped, remove the four springs (A), the two springs (B), the two springs (C), and the four screws.
2. To remove the upper frame, open it on the fulcrum A.
3. While lifting the carriage mechanism, remove the three dampers.
4. With the frames removed, insert the connectors coming from the main unit and eject the disc.

Caution: Before installing the carriage mechanism in the frames, be sure to apply some alcohol to the dampers and set the mechanism to the clamp mode.



● Removing the Pickup Unit

1. Apply shorting solder to the Pickup flexible cable. Disconnect the cable.
2. Set the mechanism to the clamp mode.
3. Remove the lead wires from the inner holder.
4. Remove the washer, styling holder, change arm, and pickup lock arm.
5. While releasing from the hook of the inner holder, lift the end of the feed screw.

Caution: In assembling, move the planet gear to the load/eject position before setting the feed screw in the inner holder.





7.1.2 CONNECTOR FUNCTION DESCRIPTION



7.2 IC

PD5928A
NJM4580V
PCM1742KE
HA12240FP
NJM2112V
S-80835CNMC-B8U
NJM2872F05
AK7730VT
PD5943A
PD8126A
TC7WH32FK
PD6468A
PE5423A
UPD63761GJ
S-812C33AUA-C2N
BA5835FM
S-L2980A15MC-C6A

● **Pin Functions(PD5928A)**

Pin No.	Pin Name	I/O	Function and Operation
1	SYSPW	O	System power control output
2	DSPPW	O	DSP : Power control output
3	DSPOUT	O	DSP : Data output
4	DSPIN	I	DSP : Data input
5	DSPCK	O	DSP : Clock output
6	BYTE		External data bus width change input
7	CNVSS		Processor mode change input
8	TELIN	I	Telephone mute input
9	NC		Not used
10	$\overline{\text{RESET}}$	I	Reset input
11	XOUT	O	Clock output
12	VSS		GND
13	XIN	I	Clock input
14	VDD		Power supply input
15	$\overline{\text{NMI}}$		Not used
16	NC		Not used
17	NC		Not used
18	NC		Not used
19	RX2	I	IP-BUS : Data input 2
20	OELPW	O	OEL power supply output
21	NC		Not used
22	PEE	O	PEE sound output
23	CSENSOUT	O	Flap open/close output
24	$\overline{\text{BRST}}$	O	P-BUS : Reset output
25	$\overline{\text{BRXEN}}$	I/O	P-BUS : Reception enable input / output
26	$\overline{\text{BSRQ}}$	I	P-BUS : Service request input
27	RX	I	IP-BUS : Data input
28	TX	O	IP-BUS : Data output
29	BSO	O	P-BUS : Data output
30	BSI	I	P-BUS : Data input
31	BSCK	O	P-BUS : Clock output
32	DSPMOD	I	DSP : STD / NW select input
33	DPDT	O	Display data output
34	KYDT	I	Key data input
35, 36	ROT1, 0	I	Rotary encoder pulse input1, 0
37	PCL	O	Output for clock adjustment
38	SWVDD	O	GRILLE : Chip enable output
39	KEYD	I	Wired remote control input
40	FLPILM	O	Inside of flap illumination output
41	ILMPW	O	Illumination output
42	EJTIN	I	Eject key input
43	GDTC1	O	Picture rewriting output 1
44	NC		Not used
45	NC		Not used
46	NC		Not used
47	$\overline{\text{GDTC2}}$	O	Picture rewriting output 2
48,49	NC		Not used
50	FOPNSW	I	Flap open sense input
51	FCLSSW	I	Flap close sense input
52	FLPCLS	O	Flap motor close output
53	FLPOPN	O	Flap motor open output

Pin No.	Pin Name	I/O	Function and Operation
54	FLPPW	O	Flap motor driver power ON/OFF output
55	NC		Not used
56	DSPCS	O	DSP : Interface chip select output
57	DSPRQ	O	DSP : Interface request output
58	DSPRDY	I	DSP : Data write ready signal input
59	DSPDRDY	I	DSP : Data read ready signal input
60	VCC		Power supply input
61	EVOLCS	O	Electronic volume chip select output
62	VSS		GND
63	LRCKOK	I	DSP : Clock stable information input
64	MCKRQ	I	Master clock request input
65	EMPIN	I	CD emphasis information input
66	SMODE	I	Slave / master select input
67	NC		Not used
68	DALMON	O	For consumption current reduction output
69	$\overline{\text{TUNPCE2}}$	O	TUNER : Chip enable output(EEPROM)
70	TUNPCE1	O	TUNER : Chip enable output(PLL)
71	ROMCS	O	ROM correction chip select output
72	ASENS	I	ACC sense input
73	BSENS	I	Back up sense input
74	ROMCK	O	ROM correction clock output
75	ROMDATA	I/O	ROM correction data input/output
76	NC		Not used
77	INTRST	O	DSP : System reset output
78	DSPRST	O	DSP : Reset output
79	IPPW	O	IPBUS : Driver power supply control output
80	ASENBO	O	IPBUS : Slave ACC sense output
81	$\overline{\text{ISENS}}$	I	Illumination sense input
82,83	MODEL1,2	I	Model select input
84	NC		Not used
85	MUTE	O	System mute output
86	TESTIN	I	Test program input
87-90	NC		Not used
91	DSENS	I	Detach sense input
92	KEYAD	I	Wired remote control input
93	ASLIN	I	ASL input
94	AVSS		AD translation power supply input terminal
95	SL	I	TUNER : Signal level input
96	VREF		A/D converter reference voltage
97	AVCC		A/D converter power supply input terminal
98	TUNPDI	I	TUNER : PLL communication data input
99	TUNPDO	O	TUNER : Data output(PLL)
100	TUNPCK	O	TUNER : Clock output(PLL)

* PD5928A



* NJM4580V



IC's marked by * are MOS type.
Be careful in handling them because they are very liable to be damaged by electrostatic induction.

PCM1742KE



HA12240FP



● Pin Functions(AK7730VT)

Pin No.	Pin Name	I/O	Function and Operation
1	EESEL	I	Control Mode select pin (Pull down)
2	JX0/SDIN4A	I	External conditional jump pin / DSP serial data input pin (Pull down)
3, 4	SDIN3, 2/JX1, 2	I	DSP serial data input pin / External condition jump pin (Pull down)
5	SDIN1	I	DSP serial data input pin (Pull down)
6	CKS1	I	Master clock (XTI) select pin (Pull down)
7	BVSS		Silicon substrate potential 0V
8	DVSS		Ground pin for digital section 0.0V
9	DVDD		Power supply pin for digital section 3.3V (typ)
10-13	SDOUT4-1	O	DSP Serial data output pin
14	BITCLK_I	I	Serial bit clock input pin
15	LRCLK_I	I	LR channel select clock input pin
16	BITCLK_O	O	Serial bit clock output pin
17	LRCLK_O	O	LR channel select clock output pin
18	RDY	O	Data write ready output pin for microcomputer interface
19	DRDY	O	Output data ready pin for Microcomputer interface
20	$\overline{CS}$	I	Chip select pin for Microcomputer interface (pull down)
21	DVDD		Power supply pin for digital section 3.3V (typ)
22	DVSS		Ground pin for digital section 0V
23, 24	CLKO1, 2	O	Clock output pin
25	XTO	O	Crystal oscillator output pin
26	XTI	I	Master clock input pin
27	DVSS		Ground pin for digital section 0V
28	DVDD		Power supply pin for digital section 3.3V (typ)
29	SMODE	I	Slave / Master mode selector pin
30	SO	O	Serial data output pin for Microcomputer interfaces
31	SI	I	Microcomputer interface serial data input and serial data output control pin
32	SCLK	I	Microcomputer interface serial data clock pin
33	$\overline{RQ}$	I	Microcomputer interface write request pin
34	$\overline{S\_RESET}$	I	System Reset pin
35	$\overline{INIT\_RESET}$	I	Reset pin (for initialization)
36	CKS0	I	Master clock (XTI) select pin (pull down)
37	LFLT		Filter connection pin for PLL
38	AVSS		Analog ground 0V
39, 40	AVDD		Power supply pin for analog section 3.3V (typ)
41	VREFH	I	Analog reference voltage input pin
42	VCOM	O	Common voltage
43	VREFL	I	Analog reference voltage input pin for low-level
44	AVSS		Analog ground 0V
45	AINR-	I	ADC Rch analog inverted input pin
46	AINR+	I	ADC Rch analog non-inverted input pin
47	AINL-	I	ADC Lch analog inverted input pin
48	AINL+	I	ADC Lch analog non-inverted input pin

* AK7730VT



NJM2112V



NJM2872F05



*S-80835CNMC-B8U



● Pin Functions (PD5943A)

Pin No.	Pin Name	I/O	Format	Function and Operation
1	$\overline{\text{ROMCS}}$	O		Not used OPEN
2	$\overline{\text{FLSTBY}}$	O		Not used OPEN
3	$\overline{\text{FL120N}}$	O		Not used OPEN
4	$\overline{\text{FLBUSY}}$	I		Flash memory busy input
5	REM	I		Remote control reception input
6	BYTE	I		GND connection
7	CNVSS	I		GND connection
8, 9	NC			Not used OPEN
10	$\overline{\text{RESET}}$	I		Pull up
11	XOUT	O		Crystal oscillating element connection pin
12	VSS1			GND connection
13	XIN	I		Crystal oscillating element connection pin
14	VCC1			VDD connection
15	$\overline{\text{NMI}}$	I		Pull up
16,17	ROT1,ROT2	I		Rotary encoder pulse input
18,19	NC			Not used
20	CD_DATA	O	C	Cathode driver pulse output
21	NC			Not used OPEN
22	CKC	O	C	Cathode driver pulse output
23	NC			Not used OPEN
24	LS	O	C	Line synchronous signal
25	NC			Not used OPEN
26	CKD	O	C	Data transfer and driver clock output
27	DPDT	I		Display data communication input
28	KYDT	O	N	Key data communication output
29	D1_L	O	C	Display data MSB output
30	NC			Not used
31	CLK1	I		UART1 clock input
32	ILMD	O	C	Dual illumination output
33	D0_L	O	C	Display data LSB output
34	NC			Not used
35	CLK0	I		UART0 clock input
36	NC	O		Not used OPEN
37	$\overline{\text{READY}}$	I		Not used Pull up
38	NC			Not used OPEN
39	$\overline{\text{HOLD}}$	I		Pull up
40	NC			OPEN
41	BCLK			Not used Pull up
42	$\overline{\text{RD}}$	O	C	Read strobe output
43	NC			OPEN
44	$\overline{\text{WR}}$	O	C	Not used OPEN
45-48	$\overline{\text{CS3}}$-$\overline{\text{CS0}}$	O	C	External ROM chip select output
49	A19	O	C	Address bus 19 output
50	NC	O	C	OPEN
51-59	A17-9	O	C	Address bus 17-9 output
60	VCC2			VDD connection
61	A8	O	C	Address bus 8 output
62	VSS2			GND connection
63-69	A7-1	O	C	Address bus 7-0 output
70	NC	O	C	OPEN
71-86	D15-0	I/O	C	Data bus 15-0 input / output
87-90	$\overline{\text{KD1}}$-$\overline{\text{KD4}}$	I	C	Key data input
91-93	$\overline{\text{KS1}}$-$\overline{\text{KS3}}$	O	C	Key strobe output
94	AVSS			GND connection
95	$\overline{\text{FL12ON}}$	O	C	Not used OPEN
96	VREF			GND connection
97	AVCC			VCC connection
98	ROMDT	I/O		Not used
99	NC			OPEN
100	ROMCK	O		Not used

* PD5943A



Format	Meaning
C	CMOS
N	Nch open drain

* PD8124A



* TC7WH32FK



* PD6468A


A15 1
A14 2
A13 3
A12 4
A11 5
A10 6
A9 7
A8 8
NC 9
NC 10
WE 11
RESET 12
NC 13
NC 14
RY/BY 15
NC 16
A17 17
A7 18
A6 19
A5 20
A4 21
A3 22
A2 23
A1 24
48 A16
47 BYTE
46 VSS
45 DQ15/A1
44 DQ7
43 DQ14
42 DQ6
41 DQ13
40 DQ5
39 DQ12
38 DQ4
37 VCC
36 DQ11
35 DQ3
34 DQ10
33 DQ2
32 DQ9
31 DQ1
30 DQ8
29 DQ0
28 OE
27 VSS
26 CE
25 A0
A0-A17 : Address input
DQ0-DQ15 : Data output
CE : Chip enable input
OE : Output enable input
WE : Write enable input
RY/BY : Ready / Busy output

● Pin Functions(PE5423A)

Pin No.	Pin Name	I/O	Format	Function and Operation
1	AVREF			A power supply Positive power supply(5V)
2	AVSS			A power supply GND
3	RFOK	O	C	Output of state of RFOK
4	CLAMP	I	C	CLAMP SW sense input
5	EVDD			E power supply Positive power supply
6	PWM			For changer(PWM)
7	NC			Not used
8	IC/FLMD0			IC : VSS direct connection/FLMOD0 : Pull-down
9	VDD			Positive power supply(5V)
10	REGC			Connected to the capacity stabilizing output of the regulator
11	VSS			GND
12	X1	I		Oscillator connection for mainclock
13	X2			Oscillator connection for mainclock
14	$\overline{\text{RESET}}$	I		System reset input
15	XT1	I		Connected to the oscillator for subclock (connected to VSS via the resistor)
16	XT2			Connected to the oscillator for subclock(Open)
17	PULLDOWN	I		Connected to EVDD or EVSS via the resistor
18	$\overline{\text{EJSW}}$	I	C	Eject key input
19	$\overline{\text{XINT}}$		C	CD LSI interruption signal input
20	NC			Not used
21	$\overline{\text{BRST}}$	I		P-Bus reset input
22	BSI	I		P-Bus serial data input
23	BSO	O	C	P-Bus serial data output
24	$\overline{\text{BSCK}}$	I/O	/C	P-Bus serial clock input/output
25	FTXD	O	C	For flash rewriting(transmitted signal)
26	FRXD	I		For flash rewriting(received signal)
27	BRXEN	I/O	/C	It is possible to receive P-Bus
28	$\overline{\text{BSRQ}}$	I/O	/C	P-Bus service request demand
29	$\overline{\text{DSPOK}}$	I		DSP microcomputer initialization OK input
30	DSCSNS(S903)	I		Disc state sense input
31	8EJ(S905)	I		Input of detection of 8 cm disc ejection
32	12EJ(S904)	I		Input of detection of 12 cm disc ejection
33	EVSS			E power supply GND
34	EVDD			E power supply Positive power supply
35, 36	SRAMLEVEL0, 1	O	C	SRAM level meter output
37	EMPH	O	C	Emphasis information output
38	$\overline{\text{EMPH}}$	O	C	Emphasis information output
39-42	NC			Not used
43	$\overline{\text{ADENA}}$	O	C	A/D reference voltage supply control output
44	LRCKOK	O	C	(DOUT mute output)
45	SRAMLEVEL2	O	C	SRAM level meter output
46	CD3VON	O	C	CD +3.3V power supply control output
47	CONT	O	C	Servo driver power supply control output
48	$\overline{\text{XRST}}$	O	C	CD LSI reset control output
49	VDCONT	O	C	VD power supply control output
50	ROMDATA	I/O	/C	E2PROM data input/output
51	ROMCS	O	C	E2PROM chip selection output
52	ROMCK	O	C	E2PROM clock output
53	LOEJ	O	C	The direction change output of LOAD/EJECT
54	CLCONT	O	C	Driver input change output
55	CDMUTE	O	C	CD mute control output
56-58	INT			For changer(Interruption at the edge)
59	$\overline{\text{XCS}}$	O	C	CD LSI chip selection output
60	NC			Not used
61	$\overline{\text{XWAIT}}$	I		CD LSI write control signal output
62	CLKOUT	O	C	Internal system clock output(Open)
63	LOCK	I		Spindle lock input
64	NC			Not used
65	$\overline{\text{XWRITE}}$	O		CD LSI write control signal output

Pin No.	Pin Name	I/O	Format	Function and Operation
66	NC			Not used
67	$\overline{\text{XREAD}}$	O		CD LSI read control signal output
68	XASTB	O		CD LSI address strobe output
69	BVSS			B power supply GND
70	BVDD			B power supply Positive power supply
71-86	AD0-15	I/O	/C	Address/data Bus 0-15
87-90	NC			Not used
91-93	A/D			For changer(A/D)
94	$\overline{\text{CSENS}}$	I		Flap closing sense input
95	TYPE_A/D	I		CD-DA analog/digital output change setup
96	$\overline{\text{TESTIN}}$	I		Chip check test program starting input
97	HOME	I		Home SW sense input
98	TEMP			Temperature information sense input
99	VDSENS			VD power supply short sense input
100	NC			Not used

* PE5423A



Format	Meaning
C	CMOS

● Pin Functions(UPD63761GJ)

Pin No.	Pin Name	I/O	Function and Operation
1	D.VDD		Power supply for digital circuits
2	D1.GND		GND for 1.6V digital circuits
3	$\overline{\text{RESET}}$	I	Input of reset
4-8	AB12-8	I	Address bus 12-8 from the microcomputer
9-16	AD7-0	I/O	Address/data bus 7-0 to the microcomputer
17	$\overline{\text{CS}}$	I	Chip selection
18	ASTB	I	Address strobe
19	$\overline{\text{READ}}$	I	Control signals(read)
20	$\overline{\text{WRITE}}$	I	Control signals(write)
21	$\overline{\text{WAIT}}$	O	Control signals(wait)
22	INTQ	O	Interruption signals to the external microcomputer
23, 24	IFMODE0, 1	I	Switching the microcomputer I/F 0, 1
25	D1.VDD		Power supply for 1.6V digital circuits
26	DA.VDD		Power supply for DAC
27	ROUT	O	Output of audio for the right channel
28	DA.GND		GND for DAC
29	REGC		Connected to the capacitor for band gap
30	DA.GND		GND for DAC
31	LOUT	O	Output of audio for the left channel
32	DA.VDD		Power supply for DAC
33	X.VDD		Power supply for the crystal oscillator
34	XTAL	I	Connected to the crystal oscillator(16.9344MHz)
35	$\overline{\text{XTAL}}$	O	Connected to the crystal oscillator(16.9344MHz)
36	X.GND		Ground for the crystal oscillator
37	VDDREG15		Control of 1.6V regulator
38	PWMSW0	I	Setup 0 for PWM output(SD, MD)
39-41	TEST3-1	I	Connected to GND
42	PWMSW1	I	Setup 1 for PWM output(FD, TD)
43	TESTEN	I	Connected to GND
44	D1.GND		GND for 1.6V digital circuits
45	DIN	I	Input of audio data
46	DOUT	O	Output of audio data
47	SCKIN	I	Clock input for audio data
48	SCKO	O	Clock output for audio data
49	LRCKIN	I	Input of LRCK for audio data
50	LRCK	O	Output LRCK for audio data
51	$\overline{\text{XTALEN}}$	I	Permission to oscillate 16.9344MHz
52	D1.VDD		Power supply for 1.6V digital circuits
53	RFCK/HOLD	O	Output of RFCK/HOLD signal
54	WFCK/MIRR	O	Output of WFCK/MIRR signal
55	PLCK	O	Output of PLCK
56	LOCK/RFOK	O	Output of LRCK/Output of RFOK
57	C1D1/C8M	O	Information on error correction/C8M : 8MHz
58	C1D2/C16M	O	Information on error correction/C16M : 16MHz
59	C2D1/RMUTE	O	Information on error correction/Mute for Rch
60	C2D2/LMUTE	O	Information on error correction/Mute for Lch
61	C2D3/SHOCK	O	Information on error correction/Detection of vibration
62	D1.GND		GND for 1.6V digital circuits
63	C33M	O	Output of 33.8688MHz(CLK for SDRAM)
64	($\overline{\text{RCS}}$)	O	DRAM $\overline{\text{CS}}$
65	RA11	O	Output of DRAM address 11
66	(CKE)	O	Output of DRAM CKE
67	$\overline{\text{RAS}}$	O	Output of DRAM $\overline{\text{RAS}}$
68	$\overline{\text{CAS0}}$(LDQM)	O	Output of DRAM lower $\overline{\text{CAS}}$(LDQM)
69	$\overline{\text{CAS1}}$(UDQM)	O	Output of DRAM upper $\overline{\text{CAS}}$(UDQM)
70	$\overline{\text{WE}}$	O	Output of DRAM $\overline{\text{WE}}$
71	$\overline{\text{OE}}$($\overline{\text{CAS}}$)	O	Output of DRAM $\overline{\text{OE}}$($\overline{\text{CAS}}$)
72	D.GND		Ground for digital circuits
73-88	RDB0-15	I/O	Input/output of DRAM data0-15
89-99	RA0-10	O	Output of DRAM address0-10

Pin No.	Pin Name	I/O	Function and Operation
100	D.VDD		Power supply for digital circuits
101	FD+	O	Output of focus drive PWM +
102	FD-	O	Output of focus drive PWM -
103	TD+	O	Output of tracking drive PWM +
104	TD-	O	Output of tracking drive PWM -
105	SD+	O	Output of thread drive PWM +
106	SD-	O	Output of thread drive PWM -
107	MD+	O	Output of spindle drive PWM +
108	MD-	O	Output of spindle drive PWM -
109	REFOUTSV	O	REFOUT for servo
110	AD.VDD		Power supply for ADC
111	EFM	O	Output of EFM signals
112	ASY	I	Input of asymmetry
113	ATEST	O	Analog tests
114	RFI	I	Input of RF
115	AD.GND		Ground for the analog system
116	AGCO	O	Output of RF
117	C3T	O	Connection to the capacitor for detecting 3T
118	AGCI	I	Input of AGC
119	RFO	O	Output of RF(AGC)
120, 121	EQ2, 1	I	Equalizer 2, 1
122	RF2-	I	Reversal input of RF2
123	RF-	I	Reversal input of RF
124	A.GND		Ground for the analog system
125	A	I	Input of A
126	C	I	Input of C
127	B	I	Input of B
128	D	I	Input of D
129	F	I	Input of F
130	E	I	Input of E
131	VREFIN	I	Input of reference voltage
132	A.VDD		Power supply for the analog system
133	REFOUT	O	Output of reference voltage
134	REFC	I	Connected to the capacitor for output of REFOUT
135	FE-	I	Reversal input of FE
136	FEO	O	Output of FE
137	ADIN	I	Input of FE, TE A/D converter
138	TE-	I	Reversal input of TE
139	TEO	O	Output of TE
140	TE2	O	TE2
141	TEC	I	TEC
142	LD	O	Output of LD
143	PD	I	Input of PD
144	D.GND		Ground for digital circuits

* UPD63761GJ



* S-812C33AUA-C2N



● Pin Functions(BA5835FM)

Pin No.	Pin Name	Function and Operation
1	VR	Input pin for reference voltage
2	OPIN2(+)	Input pin for non-inverting input for CH2 preamplifier
3	OPIN2(-)	Input pin for inverting input for CH2 preamplifier
4	OPOUT2	Output pin for CH2 preamplifier
5	OPIN1(+)	Input pin for non-inverting input for CH1 preamplifier
6	OPIN1(-)	Input pin for inverting input from CH1 preamplifier
7	OPOUT1	Output pin for CH1 preamplifier
8	GND	Ground pin
9	MUTE	Mute control pin
10	POWVCC1	Power supply pin for CH1, CH2, and CH3 at "Power" stage
11	VO1(-)	Driver CH1 - Negative output
12	VO1(+)	Driver CH2 - Positive output
13	VO2(-)	Driver CH2 - Negative output
14	VO2(+)	Driver CH2 - Positive output
15	VO3(+)	Driver CH2 - Positive output
16	VO3(-)	Driver CH2 - Negative output
17	VO4(+)	Driver CH4 - Positive output
18	VO4(-)	Driver CH4 - Negative output
19	POWVCC2	Power supply pin for CH4 at "Power" stage
20	GND	Ground pin
21	CNT	Control pin
22	LDIN	Loading input
23	OPOUTSL	Output pin for preamplifier for thread
24	OPINLSL	Input pin for preamplifier for thread
25	OPOUT3	CH3 preamplifier output pin
26	OPIN3(-)	Input pin for inverting input for CH3 preamplifier
27	OPIN3(+)	Input pin for non-inverting input for CH3 preamplifier
28	PREVCC	PreVcc

BA5835FM



* S-L2980A15MC-C6A



● FM/AM Tuner Unit



No.	Symbol	I/O	Explain	
1	AMANT	I	AM antenna input	AM antenna input high impedance AMANT pin is connected with an all antenna by way of 4.7μH. (LAU type inductor) A series circuit including an inductor and a resistor is connected with RF ground for the countermeasure against the hum of power transmission line.
2	RFGND		RF ground	Ground of antenna block
3	FMANT	I	FM antenna input	Input of FM antenna 75Ω Surge absorber(DSP-201M-S00B) is necessary.
4	VCC		power supply	The power supply for analog block. D.C 8.4V ± 0.3V
5	SL	O	signal level	Output of FM/AM signals level
6	CE2	I	chip enable-2	Chip enable for EEPROM "Low" active
7	WC	I	write control	You can write EEPROM, when EEPROM write control is "Low". Ordinary non connection
8	CE1	I	chip enable-1	Chip enable for AF•RF "High" active
9	CK	I	clock	Clock
10	DI	I	data in	Data input
11	NC		non connection	Not used
12	OSCGND		osc ground	Ground of oscillator block
13	ROM_VDD		power supply	Power supply for EEPROM pin 13 is connected with a power supply of micro computer.
14	DO	O	data out	Data output
15	DGND		digital ground	Ground of digital block
16	NC		non connection	Not used
17	VDD_3.3		power supply	The power supply for digital block. 3.3V ± 0.2V
18	NC		non connection	Not used
19	NC		non connection	Not used
20	NC		non connection	Not used
21	NC		non connection	Not used
22	AUDIOGND		audio ground	Ground of audio block
23	L ch	O	L channel output	FM stereo "L-ch" signal output or AM audio output
24	R ch	O	R channel output	FM stereo "R-ch" signal output or AM audio output

7.3 OPERATIONAL FLOW CHART



Completes power-on operation.
(After that, proceed to each source operation)



In case of the above signal, the communication with Grille microcomputer may fail.
If the time interval is not 300msec, the oscillator may be defective.

7.4 CLEANING

Before shipping out the product, be sure to clean the following portions by using the prescribed cleaning tools:

Portions to be cleaned	Cleaning tools
CD pickup lenses	Cleaning liquid : GEM1004 Cleaning paper : GED-008

Portions to be cleaned	Cleaning tools
Fans	Cleaning paper : GED-008

8. OPERATIONS



Head unit

① **EJECT button**
Press to eject a CD from your built-in CD player.
Press and hold to open or close the front panel.

② **SOURCE button, VOLUME**
This unit is turned on by selecting a source.
Press to cycle through all the available sources.
Rotate it to increase or decrease the volume.

③ **RESET button**
Press to return to the factory settings (initial settings).

④ **MULTI-CONTROL**
Push up, down, left or right to do manual seek tuning, fast forward, reverse and track search controls. Also used for controlling functions.

⑤ **CLOCK button**
Press to change to the clock display.

⑥ **BAND/ESC button**
Press to select among three FM bands and one AM band and to cancel the control mode of functions.

⑦ **DISPLAY button**
Press to select different displays.

⑧ **1–6 buttons**
Press for preset tuning and disc number search when using a multi-CD player.

⑨ **EQ button**
Press to select various equalizer curves. ■



Remote control

Operation is the same as when using the buttons on the head unit.

⑩ VOLUME buttons

Press to increase or decrease the volume.

⑪ AUDIO button

Press to select various sound quality controls.

⑫ FUNCTION button

Press to select functions.

⑬ Joystick

Move to do manual seek tuning, fast forward, reverse and track search controls. Also used for controlling functions.

- You can perform same operation as **MULTI-CONTROL** on the head unit, except the turning operation.

⑭ DIRECT button

Press to directly select the desired track.

⑮ CLEAR button

Press to cancel the input number when **0–9** are used.

⑯ 0–9 buttons

Press to directly select the desired track, preset tuning or disc. Buttons **1–6** can operate the preset tuning for the tuner or disc number search for the multi-CD player.

⑰ TUNER button

Press to select the tuner as the source.

⑱ ATT button

Press to quickly lower the volume level, by about 90%. Press once more to return to the original volume level.

⑲ CD button

Press to select the built-in or multi-CD player as the source.

⑳ PGM button

Press to operate the preprogrammed functions for each source. ▣

Playing a CD



These are the basic steps necessary to play a CD with your built-in CD player.

① **Play time indicator**
Shows the elapsed playing time of the current track.

② **Track number indicator**
Shows the track currently playing.

③ **Disc title indicator**
Shows the title of the currently playing disc.
- If no title has been entered for the currently playing disc, nothing is displayed.

1 Press SOURCE to select the built-in CD player.
Press **SOURCE** until you see **Compact Disc** displayed.
- If no disc is loaded in the unit, you cannot select **Compact Disc** (built-in CD player). Insert a disc in the unit.

2 To perform fast forward or reverse, push and hold MULTI-CONTROL left or right.
- If you select **ROUGH**, pushing and holding **MULTI-CONTROL** left or right enables you to search every 10 tracks in the current disc.

3 To skip back or forward to another track, push MULTI-CONTROL left or right.
Pushing **MULTI-CONTROL** right skips to the start of the next track. Pushing **MULTI-CONTROL** left once skips to the start of the current track. Pushing again will skip to the previous track.

Note
When a disc is inserted, the disc and track titles automatically begin to scroll in the display. When Ever Scroll is set to ON at the initial setting, the disc and track titles scroll continuously. ▣

● CONNECTION DIAGRAM(DEH-P860MP/XN/UC)



● CONNECTION DIAGRAM(DEH-P8600MP/XN/UC)



● CONNECTION DIAGRAM(DEH-P8650MP/XN/ES)



A

B

C

D

E

F

● Jigs List

Name	Jig No.	Remarks
Test Disc	TCD-782	Checking the grating
L.P.F.		Checking the grating (Two pieces)
Extension Cable	GGD1160	Checking the keyboard unit
Extension PCB	GGD1378	Checking the keyboard unit
CD-ROM	GGV1168	OEL screensaver studio lka to lkd application
Cleaning liquid	GEM1004	Cleaning CD pickup lenses
Cleaning paper	GED-008	Cleaning CD pickup lenses